

# SOT89 PNP SILICON PLANAR MEDIUM POWER TRANSISTOR

## BCX69


ISSUE 2 – FEBRUARY 1995

### FEATURES

- \* High gain and low saturation voltages

COMPLEMENTARY TYPE – BCX68

PARTMARKING DETAIL – BCX69 – CJ  
BCX69-16 – CG  
BCX69-25 – CH



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CB0}$	-25	V
Collector-Emitter Voltage	$V_{CE0}$	-20	V
Emitter-Base Voltage	$V_{EBO}$	-5	V
Peak Pulse Current	$I_{CM}$	-2	A
Continuous Collector Current	$I_C$	-1	A
Power Dissipation at $T_{amb}=25^{\circ}\text{C}$	$P_{tot}$	1	W
Operating and Storage Temperature Range	$T_j, T_{stg}$	-65 to +150	$^{\circ}\text{C}$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown voltage	$V_{(BR)CBO}$	-25			V	$I_C = -100\mu\text{A}$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-20			V	$I_C = -10\text{mA}$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -100\mu\text{A}$
Collector Cut-Off Current	$I_{CBO}$			-0.1	$\mu\text{A}$	$V_{CB} = -25\text{V}$
Emitter Cut-Off Current	$I_{EBO}$			-10	$\mu\text{A}$	$V_{CB} = -25\text{V}, T_{amb} = 150^{\circ}\text{C}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-0.5	V	$V_{EB} = -5\text{V}$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			-1.0	V	$I_C = -1\text{A}, I_B = -100\text{mA}$
Static Forward Current Transfer Ratio	$h_{FE}$	50				$I_C = -5\text{mA}, V_{CE} = -1\text{V}$
		85		375		$I_C = -500\text{mA}, V_{CE} = -1\text{V}$
		60		250		$I_C = -1\text{A}, V_{CE} = -1\text{V}^*$
	BCX69-16	100		400		$I_C = -500\text{mA}, V_{CE} = -1\text{V}^*$
	BCX69-25	160	250			$I_C = -500\text{mA}, V_{CE} = -1\text{V}$
Transition Frequency	$f_T$	100			MHz	$I_C = -100\text{mA}, V_{CE} = -5\text{V}, f = 100\text{MHz}$
Output Capacitance	$C_{obo}$			25	pF	$V_{CB} = -10\text{V}, f = 1\text{MHz}$

\*Measured under pulsed conditions. Pulse width=300 $\mu\text{s}$ . Duty cycle  $\leq 2\%$ . For typical characteristics graphs see FMMT549 datasheet.