10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

Rev. 4 — 25 November 2011

Product data sheet

1. General description

The 74LVC827A is a 10-bit buffer/line driver with 3-state outputs. The 3-state outputs are controlled by the output enable pins $\overline{OE1}$ and $\overline{OE2}$. A HIGH on pin \overline{OEn} causes the outputs to assume a high-impedance OFF-state.

Inputs can be driven from either 3.3 V or 5 V devices. When disabled, up to 5.5 V can be applied to the outputs. These features allow the use of these devices as translators in mixed 3.3 V and 5 V applications.

2. Features and benefits

- 5 V tolerant inputs/outputs for interfacing with 5 V logic
- Wide supply voltage range from 1.2 V to 3.6 V
- CMOS low power consumption
- Direct interface with TTL levels
- Complies with JEDEC standard:
 - JESD8-7A (1.65 V to 1.95 V)
 - ◆ JESD8-5A (2.3 V to 2.7 V)
 - JESD8-C/JESD36 (2.7 V to 3.6 V)
- ESD protection:
 - HBM JESD22-A114F exceeds 2000 V
 - MM JESD22-A115B exceeds 200 V
 - CDM JESD22-C101E exceeds 1000 V
- Specified from -40 °C to +85 °C and -40 °C to +125 °C

3. Ordering information


Table 1.Ordering information

Type number	Package			
	Temperature range	Name	Description	Version
74LVC827AD	–40 °C to +125 °C	SO24	plastic small outline package; 24 leads; body width 7.5 mm	SOT137-1
74LVC827ADB	–40 °C to +125 °C	SSOP24	plastic shrink small outline package; 24 leads; body width 5.3 mm	SOT340-1
74LVC827APW	–40 °C to +125 °C	TSSOP24	plastic thin shrink small package outline package; 24 leads; body width 4.4 mm	SOT355-1

nexperia

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

4. Functional diagram




2 of 16

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

5. Pinning information

5.1 Pinning



5.2 Pin description

Table 2.	Pin description	
Symbol	Pin	Description
OE1	1	output enable input 1 (active LOW)
OE2	13	output enable input 2 (active LOW)
A[0:9]	2, 3, 4, 5, 6, 7, 8, 9, 10, 11	data input
Y[0:9]	23, 22, 21, 20, 19, 18, 17, 16, 15, 14	data output
GND	12	ground (0 V)
V _{CC}	24	supply voltage

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

6. Functional description

Table 3. Function table^[1]

		Input	Output
OE1	OE2	An	Yn
L	L	L	L
L	L	Н	Н
Х	Н	Х	Z
Н	Х	Х	Z

[1] H = HIGH voltage level

L = LOW voltage level

X = don't care

Z = high-impedance OFF-state

7. Limiting values

Table 4.Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

					,
Symbol	Parameter	Conditions	Min	Max	Unit
V _{CC}	supply voltage		-0.5	+6.5	V
VI	input voltage		<u>[1]</u> –0.5	+6.5	V
Vo	output voltage	output HIGH or LOW state	[2] -0.5	V _{CC} + 0.5	V
		output 3-state	[2] -0.5	+6.5	V
I _{IK}	input clamping current	V ₁ < 0 V	-50	-	mA
Ι _{ΟΚ}	output clamping current	$V_{O} > V_{CC}$ or $V_{O} < 0$ V	-	±50	mA
l _O	output current	$V_{O} = 0 V$ to V_{CC}	-	±50	mA
I _{CC}	supply current		-	100	mA
I _{GND}	ground current		-100	-	mA
T _{stg}	storage temperature		-65	+150	°C
P _{tot}	total power dissipation	$T_{amb} = -40 \ ^{\circ}C \ to \ +125 \ ^{\circ}C$	<u>[3]</u>	500	mW

[1] The minimum input voltage ratings may be exceeded if the input current ratings are observed.

[2] The output voltage ratings may be exceeded if the output current ratings are observed.

[3] SO24 package: P_{tot} derates linearly with 8 mW/K above 70 °C.

(T)SSOP24 package: P_{tot} derates linearly with 5.5 mW/K above 60 °C.

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

8. Recommended operating conditions

Table 5.	Recommended operating cond	itions			
Symbol	Parameter	Conditions	Min	Max	Unit
V _{CC}	supply voltage		1.65	3.6	V
		functional	1.2		V
VI	input voltage		0	5.5	V
Vo	output voltage	output HIGH or LOW state	0	V _{CC}	V
		output 3-state	0	5.5	V
T _{amb}	ambient temperature		-40	+125	°C
$\Delta t / \Delta V$	input transition rise and fall rate	V_{CC} = 1.65 V to 2.7 V	0	20	ns/V
		$V_{CC} = 2.7 \text{ V} \text{ to } 3.6 \text{ V}$	0	10	V V V V V V °C

9. Static characteristics

Table 6. Static characteristics

At recommended operating conditions. Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	-40	°C to +8	85 °C	–40 °C to	o +125 ℃	Unit
			Min	Typ <mark>[1]</mark>	Max	Min	Max	
V _{IH}	HIGH-level	V _{CC} = 1.2 V	1.08	-	-	1.08	-	V
input vo	input voltage	V_{CC} = 1.65 V to 1.95 V	$0.65 \times V_{CC}$	-	-	$0.65 \times V_{CC}$	-	V
		V_{CC} = 2.3 V to 2.7 V	1.7	-	-	1.7	-	V
		V_{CC} = 2.7 V to 3.6 V	2.0	-	-	2.0	-	V
V _{IL} LOW-level input voltage	V _{CC} = 1.2 V	-	-	0.12	-	0.12	V	
	V_{CC} = 1.65 V to 1.95 V	-	-	$0.35 \times V_{CC}$	-	$0.35 \times V_{CC}$	V	
	V_{CC} = 2.3 V to 2.7 V	-	-	0.7	-	0.7	V	
	$V_{CC} = 2.7 \text{ V to } 3.6 \text{ V}$	-	-	0.8	-	0.8	V	
V _{OH}	HIGH-level	$V_{I} = V_{IH} \text{ or } V_{IL}$						
output voltage	-	$I_{O} = -100 \ \mu A;$ $V_{CC} = 1.65 \ V \text{ to } 3.6 \ V$	$V_{CC}-0.2$	-	-	$V_{CC}-0.3$	-	V
		$I_{O} = -4 \text{ mA}; V_{CC} = 1.65 \text{ V}$	1.2	-	-	1.05	-	V
		$I_{O} = -8$ mA; $V_{CC} = 2.3$ V	1.8	-	-	1.65	-	V
		I_{O} = -12 mA; V_{CC} = 2.7 V	2.2	-	-	2.05	-	V
		$I_{O} = -18$ mA; $V_{CC} = 3.0$ V	2.4	-	-	2.25	-	V
		I_{O} = -24 mA; V_{CC} = 3.0 V	2.2	-	-	2.0	-	V
V _{OL}	LOW-level	$V_{I} = V_{IH} \text{ or } V_{IL}$						
	output voltage	$I_{O} = 100 \ \mu A;$ $V_{CC} = 1.65 \ V \text{ to } 3.6 \ V$	-	-	0.2	-	0.3	V
		$I_0 = 4 \text{ mA}; V_{CC} = 1.65 \text{ V}$	-	-	0.45	-	0.65	V
		$I_0 = 8 \text{ mA}; V_{CC} = 2.3 \text{ V}$	-	-	0.6	-	0.8	V
		$I_0 = 12 \text{ mA}; V_{CC} = 2.7 \text{ V}$	-	-	0.4	-	0.6	V
		$I_{O} = 24 \text{ mA}; V_{CC} = 3.0 \text{ V}$	-	-	0.55	-	0.8	V
lı	input leakage current	V_{CC} = 3.6 V; V_{I} = 5.5 V or GND	-	±0.1	±5	-	±20	μA
74LVC827A		All information provided in t	his document is subjec	t to legal discla	aimers.	© Ne	experia B.V. 2017. All rig	ghts reserv

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

Symbol	Parameter	Conditions	-40	°C to +8	35 °C	–40 °C t	o +125 °C	Unit
			Min	Typ[1]	Max	Min	Max	
I _{OZ}	OFF-state output current	$\label{eq:VI} \begin{array}{l} V_{I}=V_{IH} \text{ or } V_{IL}; \ V_{CC}=3.6 \ V; \\ V_{O}=5.5 \ V \text{ or } \text{GND}; \end{array}$	-	0.1	±5	-	±20	μA
I _{OFF}	power-off leakage current	V_{CC} = 0 V; V _I or V _O = 5.5 V	-	0.1	±10	-	±20	μA
I _{CC}	supply current	V_{CC} = 3.6 V; V_{I} = V_{CC} or GND; I_{O} = 0 A	-	0.1	10	-	40	μA
ΔI_{CC}	additional supply current	per input pin; V _{CC} = 2.7 V to 3.6 V; V _I = V _{CC} - 0.6 V; I _O = 0 A	-	5	500	-	5000	μA
CI	input capacitance	$V_{CC} = 0 V$ to 3.6 V; V ₁ = GND to V _{CC}	-	5.0	-	-	-	pF

Table 6. Static characteristics ...continued

At recommended operating conditions. Voltages are referenced to GND (ground = 0 V).

[1] All typical values are measured at V_{CC} = 3.3 V (unless stated otherwise) and T_{amb} = 25 °C.

10. Dynamic characteristics

Table 7. Dynamic characteristics

Voltages are referenced to GND (ground = 0 V). For test circuit see Figure 6.

Symbol	Parameter	Conditions		T _{amb} =	–40 °C to	+85 °C	–40 °C to	• +125 °C	Unit
				Min	Typ <mark>[1]</mark>	Max	Min	Max	ns ns ns ns ns ns ns ns ns ns ns ns ns n
t _{pd}	propagation	An to Yn; see Figure 4	[2]						
	delay	$V_{CC} = 1.2 V$		-	15	-	-	-	ns
		V_{CC} = 1.65 V to 1.95 V		1.5	6.4	15.5	1.5	17.9	ns
		V_{CC} = 2.3 V to 2.7 V		1.0	3.4	8.0	1.0	9.3	ns
		$V_{CC} = 2.7 V$		1.5	3.4	7.1	1.5	9.0	ns
		$V_{CC} = 3.0 \text{ V} \text{ to } 3.6 \text{ V}$		1.0	2.9	6.7	1.0	8.5	ns
t _{en}	enable time	OEn to Yn; see Figure 5	[2]						
		$V_{CC} = 1.2 V$		-	20	-	-	-	ns
		V_{CC} = 1.65 V to 1.95 V		1.8	7.9	16.7		19.3	ns
		V_{CC} = 2.3 V to 2.7 V		1.5	4.4	9.2	1.5	10.6	ns
		$V_{CC} = 2.7 V$		1.5	4.5	8.5	1.5	11.0	ns
		V_{CC} = 3.0 V to 3.6 V		1.0	3.5	7.3	1.0	9.5	ns
t _{dis}	disable time	OEn to Yn; see Figure 5	[2]						
		$V_{CC} = 1.2 V$		-	10.0	-	-	-	ns
		V_{CC} = 1.65 V to 1.95 V		2.5	4.3	11.3	2.5	13.0	ns
		V_{CC} = 2.3 V to 2.7 V		1.0	2.4	6.4	1.0	7.4	ns
		$V_{CC} = 2.7 V$		1.5	3.2	7.3	1.5	9.5	ns
		V_{CC} = 3.0 V to 3.6 V		1.5	3.0	6.7	1.5	8.5	ns
t _{sk(o)}	output skew time	V_{CC} = 3.0 V to 3.6 V	[3]	-	-	1.0	-	1.5	ns

74LVC827A

Product data sheet

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

Symbol	Parameter	Conditions		T _{amb} =	–40 °C to	+85 °C	–40 °C to	o +125 ℃	Unit
				Min	Typ <mark>[1]</mark>	Max	Min	Max	
C _{PD} power dissipation capacitance	per input; $V_I = GND$ to V_{CC}	[4]							
	V_{CC} = 1.65 V to 1.95 V		-	5.5	-	-	-	pF	
	V_{CC} = 2.3 V to 2.7 V		-	8.8	-	-	-	pF	
		V_{CC} = 3.0 V to 3.6 V		-	11.7	-	-	-	pF

Table 7. Dynamic characteristics ...continued

Voltages are referenced to GND (ground = 0 V). For test circuit see Figure 6.

[1] Typical values are measured at T_{amb} = 25 °C and V_{CC} = 1.2 V, 1.8 V, 2.5 V, 2.7 V, and 3.3 V respectively.

 t_{dis} is the same as t_{PLZ} and t_{PHZ} .

[3] Skew between any two outputs of the same package switching in the same direction. This parameter is guaranteed by design.

[4] C_{PD} is used to determine the dynamic power dissipation (P_D in μ W).

 $P_{D} = C_{PD} \times V_{CC}^{2} \times f_{i} \times N + \Sigma (C_{L} \times V_{CC}^{2} \times f_{o}) \text{ where:}$

 f_i = input frequency in MHz; f_o = output frequency in MHz

 C_L = output load capacitance in pF


 V_{CC} = supply voltage in Volts

N = number of inputs switching

 $\Sigma(C_L \times V_{CC}{}^2 \times f_o)$ = sum of the outputs

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

11. Waveforms






Table 8. Measurement points

Supply voltage	Input	Output			
V _{CC}	V _M	V _M	V _X	V _Y	
< 2.7 V	$0.5 imes V_{CC}$	$0.5 imes V_{CC}$	V _{OL} + 0.1 V	V _{OH} – 0.1 V	
≥ 2.7 V	1.5 V	1.5 V	V _{OL} + 0.3 V	V _{OH} – 0.3 V	

74LVC827A

Nexperia

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state




Table	9.	Test	data

Supply voltage	Input		Load		V _{EXT}		
	VI	t _r , t _f	CL	RL	t _{PLH} , t _{PHL}	t _{PLZ} , t _{PZL}	t _{PHZ} , t _{PZH}
1.2 V	V _{CC}	\leq 2 ns	30 pF	1 kΩ	open	$2 \times V_{CC}$	GND
1.65 V to 1.95 V	V _{CC}	\leq 2 ns	30 pF	1 kΩ	open	$2\times V_{CC}$	GND
2.3 V to 2.7 V	V _{CC}	\leq 2 ns	30 pF	500 Ω	open	$2\times V_{CC}$	GND
2.7 V	2.7 V	\leq 2.5 ns	50 pF	500 Ω	open	$2 \times V_{CC}$	GND
3.0 V to 3.6 V	2.7 V	\leq 2.5 ns	50 pF	500 Ω	open	$2\times V_{CC}$	GND

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

12. Package outline




Fig 7. Package outline SOT137-1 (SO24)

All information provided in this document is subject to legal disclaimers.

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state




Fig 8. Package outline SOT340-1 (SSOP24)

All information provided in this document is subject to legal disclaimers.

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state




Fig 9. Package outline SOT355-1 (TSSOP24)

All information provided in this document is subject to legal disclaimers.

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

13. Abbreviations

Table 10. Abbreviations				
Acronym	Description			
CDM	Charged Device Model			
DUT	Device Under Test			
ESD	ElectroStatic Discharge			
HBM	Human Body Model			
MM	Machine Model			
TTL	Transistor-Transistor Logic			

14. Revision history

Table 11. Revision history					
Document ID	Release date	Data sheet status	Change notice	Supersedes	
74LVC827A v.4	20111125	Product data sheet	-	74LVC827A v.3	
Modifications:		s for t _{pd} , t _{en} and t _{dis} in <u>Table</u> ographical errors	7 "Dynamic characteris	tics"	
74LVC827A v.3	20111103	Product data sheet	-	74LVC827A v.2	
Modifications:	 The format of this document has been redesigned to comply with the new identity guidelines of NXP Semiconductors. 				
	 Legal texts ha 	ve been adapted to the new	company name where	appropriate.	
	• <u>Table 4, Table</u>	5, Table 6, Table 7, and Tab	ole 9: values added for l	ower voltage ranges.	
	 Added: type n 	umber 74LVC827ABQ (DH\	/QFN24 package)		
74LVC827A v.2	20040408	Product specification	-	74LVC827A v.1	
74LVC827A v.1	19980904	Product specification	-	-	

15. Legal information

15.1 Data sheet status

Document status[1][2]	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nexperia.com.

15.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any

representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and

customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

15.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of Nexperia.

Right to make changes — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of a Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia accepts no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale - Nexperia

products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nexperia.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

74LVC827A

Product data sheet

Nexperia

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

Non-automotive qualified products — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of

non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond

16. Contact information

Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

15.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

For more information, please visit: http://www.nexperia.com

For sales office addresses, please send an email to: salesaddresses@nexperia.com

Nexperia

74LVC827A

10-bit buffer/line driver with 5 V tolerant inputs/outputs; 3-state

17. Contents

General description 1
Features and benefits 1
Ordering information 1
Functional diagram 2
Pinning information 3
Pinning 3
Pin description 3
Functional description 4
Limiting values 4
Recommended operating conditions 5
Static characteristics 5
Dynamic characteristics 6
Waveforms
Package outline 10
Abbreviations
Revision history 13
Legal information 14
Data sheet status 14
Definitions 14
Disclaimers 14
Trademarks 15
Contact information 15
Contents 16

© Nexperia B.V. 2017. All rights reserved

For more information, please visit: http://www.nexperia.com For sales office addresses, please send an email to: salesaddresses@nexperia.com Date of release: 25 November 2011