
**ON Semiconductor** 

Is Now

# Onsemi

To learn more about onsemi<sup>™</sup>, please visit our website at <u>www.onsemi.com</u>

onsemi and ONSEMI: and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product factures, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application is the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application, Buyer shall indemnify and hold onsemi and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application, Buyer shall indemnify and hold ons



Symbol	Parameter	Ratings	Units
V <sub>DSS</sub>	Drain to Source Voltage	40	V
V <sub>GS</sub>	Gate to Source Voltage	±20	V
	Drain Current Continuous (V <sub>GS</sub> = 10V)	50	A
ID	Pulsed	Figure 4	A
E <sub>AS</sub>	Single Pulse Avalanche Energy (Note 1)	144	mJ
р	Power Dissipation	79	W
P <sub>D</sub>	Derate above 25°C	0.53	W/ºC
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Temperature	-55 to +175	°C
$R_{\theta JC}$	Thermal Resistance Junction to Case	1.9	°C/W
$R_{ extsf{ heta}JA}$	Thermal Resistance Junction to Ambient, 1in <sup>2</sup> copper pad area	52	°C/W

# **Package Marking and Ordering Information**

Device Marking	Device	Package	Reel Size	Tape Width	Quantity
FDD8445	FDD8445-F085	TO-252AA	13"	12mm	2500 units

Notes:

1: Starting  $T_J = 25^{\circ}$ C, L = 0.18mH,  $I_{AS} = 40A$ 2: A suffix as "...F085P" has been temporarily introduced in order to manage a double source strategy as ON Semiconductor has officially announced in Aug 2014.

©2016 Semiconductor Components Industries, LLC. September-2017, Rev. 2

Publication Order Number: FDD8445-F085/D

FDD8445-F085 N-Channel PowerTrench<sup>®</sup> MOSFET


Symbol	Parameter	Test Conditio	ns Min	і Тур	Max	Units
Off Cha	racteristics					
B <sub>VDSS</sub>	Drain to Source Breakdown Voltage	$I_D = 250 \mu A, V_{GS} = 0 V$	40	-	-	V
	Zara Cata Valtaga Drain Current	$V_{\text{DS}} = 32 \text{V},$		-	1	۸
IDSS	Zero Gate Voltage Drain Current	$V_{GS} = 0V$ T	<sub>A</sub> = 150°C -	-	250	μA
I <sub>GSS</sub>	Gate to Source Leakage Current	$V_{GS} = \pm 20V$	-	-	±100	nA
V <sub>GS(th)</sub>	Gate to Source Threshold Voltage	$V_{GS} = V_{DS}, I_D = 250 \mu A$	. 2	2.8	4	V
<u>\</u>	Cata to Source Threshold Valtage		2	2.0	4	V
00(11)		$I_{\rm D} = 50$ A, $V_{\rm GS} = 10$ V	-	6.7	8.7	
r <sub>DS(on)</sub>	Drain to Source On Resistance	$I_D = 50A, V_{GS} = 10V$ $T_1 = 175^{\circ}C$		12.5	16.3	mΩ
Dynami <sub>Ciss</sub>	C Characteristics		-	3040	4050	pF
C <sub>oss</sub>	Output Capacitance	─ V <sub>DS</sub> = 25V, V <sub>GS</sub> = 0V, f = 1MHz		295	390	pF
C <sub>rss</sub>	Reverse Transfer Capacitance			178	270	pF
R <sub>G</sub>	Gate Resistance	f = 1MHz		1.7	-	Ω
-	Total Gate Charge at 10V	$V_{GS} = 0$ to 10V	-	45	59	nC
Q <sub>g(TOT)</sub>		11 01 011		5.8	7.6	nC
Q <sub>g(TOT)</sub> Q <sub>g(TH)</sub>	Threshold Gate Charge	$V_{GS} = 0$ to 2V V	<sub>DD</sub> = 20V	5.6	1.0	no
Q <sub>g(TOT)</sub> Q <sub>g(TH)</sub> Q <sub>gs</sub>	Threshold Gate Charge Gate to Source Gate Charge		<sub>DD</sub> = 20V = 50A -	12.5	-	nC

# **Switching Characteristics**


t <sub>on</sub>	Turn-On Time	$V_{DD} = 20V, I_D = 50A$ $V_{GS} = 10V, R_{GS} = 2\Omega$	-	-	138	ns
t <sub>d(on)</sub>	Turn-On Delay Time		-	10	-	ns
t <sub>r</sub>	Rise Time		-	82	-	ns
t <sub>d(off)</sub>	Turn-Off Delay Time		-	26	-	ns
t <sub>f</sub>	Fall Time		-	9.6	-	ns
t <sub>off</sub>	Turn-Off Time		-	-	53	ns

## **Drain-Source Diode Characteristics**


V <sub>SD</sub>	Source to Drain Diode Voltage	I <sub>SD</sub> = 50A	-	-	1.25	V	
		I <sub>SD</sub> = 25A	-	-	1.0	v	
t <sub>rr</sub>	Reverse Recovery Time	I <sub>SD</sub> = 50A, dI <sub>SD</sub> /dt = 100A/μs	-	-	39	ns	
Q <sub>rr</sub>	Reverse Recovery Charge		-	-	38	nC	



www.onsemi.com 3



www.onsemi.com 4



ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor haves against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death a

### PUBLICATION ORDERING INFORMATION

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

Semiconductor Components Industries, LLC