

POWER RELAY 1 POLE - 10A High sensitivity

FTR-K1 Series

■ FEATURES

• Low profile (height: 15.7mm)

High insulation

Insulation distance (between coil and contacts): 10mm min.

Dielectric strength: 5KV Surge strength: 10KV

• Low coil power (400mW)

• Cadmium free contacts

Safety standards
 UL, CSA, VDE approved

UL, CSA TV-5 rating approved (1 form A type)

• UL F class wire insulation

• Flux proof, RTII

RoHS compliant

Please see page 6 for more information



■ PARTNUMBER INFORMATION

(a)	Relay type	FTR-K1	: FTR-K1-Series
(b)	Contact configuration	A C	: 1 form A (SPST-NO) : 1 form C (SPDT)
(c)	Coil type / enclosure	L	: High sensitivity (250mW) / flux proof
(d)	Coil rated voltage	012	: 548 VDC Coil rating table at page 3
(e)	Contact material	W	: AgSnO ₂
(f)	Terminal pitch	LA LB	: 10A high sensitive (250mW) 3.5mm pitch : 10A high sensitive (250mW) 5.0mm pitch
(g)	Special type	Nil BG	: Standard type (without gold plate) : Gold plated 3 µm

Actual marking does not carry the type name: "FTR"

E.g.: Ordering code: FTR-K1ALO12W-LAActual marking: K1ALO12W-LA

SPECIFICATION

Item			FTR-K1 (A, C) L () W - (LA, LB)		
Contact Data	Configuration		1 form A, 1 form C		
	Construction		Single		
	Material		AgSnO ₂		
	Resistance (initial)		Max. 100mOhm at 1A, 6VDC		
	Contact rating (resistive	2)	10A, 250VAC		
	Max. carrying current *	1	14A		
	Max. switching voltage		440VAC		
	Max. switching power		2,500VA		
	Min. switching load *2		100mA, 5VDC		
Life	Mechanical		Min. 20 x 10 ⁶ operations		
	Electrical	AC contact rating	Min. 100 x 10 ³ operations (-LA and -LB 1 Form C) Min. 150 x 10 ³ operations (-LB 1 Form A)		
Coil Data	Rated power (20 °C)		250mW		
	Operate power (20 °C)		141mW		
	Operating temperature	range	-40 °C to +85 °C (no frost), (LB: -40 °C to +105 °C)		
Timing Data	Operate (at nominal vo	ltage)	Max. 15ms (without bounce, no diode)		
	Release (at nominal vo	ltage)	Max. 5ms (without bounce, no diode)		
Insulation	Resistance (initial)		Min. 1,000MOhm at 500VDC		
	Dielectric strength	Open contacts	1,000VAC (50/60Hz) 1min		
	biciccule strength	Contacts to coil	5,000VAC (50/60Hz) 1min		
	Surge strength	Coil to contacts	10,000V / 1.2 x 50µs standard wave		
	Clearance		10mm		
	Creepage		10mm		
	EN61810-1, VDE0435 Voltage		250V		
		Pollution degree	3		
		Material group	III a		
		Category	C / 250V (Reference voltage) (VDE0110b)		
Other	Vibration resistance	Misoperation≥1us	10 to 55 to 10Hz single amplitude 0.35mm		
	Tibidion resistance	Endurance	10 to 55 to 10Hz single amplitude 0.75mm		
	Shock	Misoperation≥1us	100m/s² (11 ± 1ms)		
		Endurance	1,000m/s² (6 ± 1ms)		
	Weight		Approximately 13g		
	Sealing		Flux proof, RTII		

^{* 1:} Need to consider the heat from PCB when max. current is more than 10A.
* 2: Minimum switching loads mentioned above are reference values. Please perform the confirmation test with actual load before production since reference values may vary according to switching frequencies, environmental conditions and expected reliability levels.

■ COIL RATING

Coil Code	Rated Coil Voltage (VDC)	Coil Resistance +/- 10% (Ohm)	Must Operate Voltage (VDC) *	Must Release- Voltage (VDC) *	Rated Power (mW)
005	5	100	3.75	0.5	
006	6	145	4.5	0.6	
009	9	325	6.75	0.9	250
012	12	575	9	1.2	
018	18	1,300	13.5	1.8	
024	24	2,310	18	2.4	
048	48	9,216	36	4.8	

Note: All values in the table are valid for 20°C and zero contact current.

* Specified operate values are valid for pulse wave voltage.


Please use at rated coil voltage. Please refer to characteristic data and set up adequate voltage in case of use at over voltage.


SAFETY STANDARDS


Туре	Compliance	Contact rating		
		1 Form A	1 Form C	
UL	UL 508	Flammability: UI	UL 94-V0 (plastics)	
	E63614	[FTR-K1AL()W-(LA/AB)] 10A, 277VAC (resistive)	[FTR-K1CL ()W-(LA/LB)] 10A, 277VAC (resistive)	
CSA	C22.2 No. 14 LR 40304	1/3hp, 125VAC 1/2hp, 277VAC Pilot duty: B300	[FTR-K1CL()W-LB] 16A, 260VAC (N.O.)	
VDE	IEC/EN61810-1 E60335-1 clause 15.3; 16.3; 29.1; 29.2; 29.3 EN60730-1 clause 12.1; 13.2; 20.1; 20.2; 20.3	[FTR-K1AL()W-(LA/LB)] 10A, 250VAC, 150,000 cycles LA: 85 °C, LB:105 °C 3A, 250VAC (cosφ=0.4), 100,000 cycles, LA: 85 °C, LB: 105 °C	10A, 250VAC, 100,000 cycles, LA: 85 °C	


3


■ CHARACTERISTIC DATA
















DIMENSIONS

FTR-K1AL()W-LA


Dimensions



Schematics




PC board mounting hole layout (BOTTOM VIEW)




FTR-K1CL()W-LA


Dimensions



Schematics



PC board mounting hole layout (BOTTOM VIEW)




Unit: mm

- * Dimensions of the terminals do not include thickness of pre-solder.
- * Tolerance of PC board mounting hole layout: ±0.1 unless otherwise specified.


DIMENSIONS

FTR-K1AL()W-LB

Dimensions




Schematics




Connect terminal #1 and #8 on the PC board

PC board mounting hole layout (BOTTOM VIEW)




FTR-K1CL()W-LB

Dimensions




Schematics



Connect terminal #1 and #8 on the PC board

PC board mounting hole layout (BOTTOM VIEW)



Unit: mm

- * Dimensions of the terminals do not include thickness of pre-solder.
- * Tolerance of PC board mounting hole layout: ±0.1 unless otherwise specified.

Cautions

- All values mentioned in this datasheet are provided under ideal conditions. Please perform the confirmation test before actual use.
- Reflow soldering is prohibited.
- Do not use relays in the atmosphere with sulfide gas, chloride gas or nitric oxide. Contact resistance may increase.
- Do not use silicon or silicon-containing product or materials near relays. It may cause contact failure.

RoHS Compliance and Lead Free Information

1. General Information

- All relays produced by Fujitsu Components are compliant with RoHS directive 2011/65/EU including amendments.
- Cadmium as used in electrical contacts is exempted from the RoHS directives.
 As per Annex III of directive 2011/65/EU.
- All relays are lead-free. Please refer to Lead-Free Status Info for older date codes at: http://www.fujitsu.com/downloads/MICRO/fcai/relays/lead-free-letter.pdf
- Lead free solder plating on relay terminals is Sn-3.0Ag-0.5Cu, unless otherwise specified. This material has been verified to be compatible with PbSn assembly process.

2. Recommended Lead Free Solder Condition

• Recommended solder Sn-3.0Ag-0.5Cu.

Flow Solder Condition:

Pre-heating: maximum 120°C

within 90 sec.

Soldering: dip within 5 sec. at

255°C ± 5°C solder bath

Relay must be cooled by air immediately

after soldering

Solder by Soldering Iron:

Soldering Iron 30-60W

Temperature: maximum 350-360°C Duration: maximum 3 sec.

We highly recommend that you confirm your actual solder conditions

3. Moisture Sensitivity

• Moisture Sensitivity Level standard is not applicable to electromechanical relays, unless otherwise indicated.

4. Tin Whiskers

• Dipped SnAgCu solder is known as presenting a low risk to tin whisker development. No considerable length whisker was found by our in house test.

Fujitsu Components International Headquarter Offices

JapanFUJITSU COMPONENT LIMITED Shinagawa Seaside Park Tower 19F,

12-4, Higashi-shinagawa 4-chome, Shinagawa-ku,

Tokyo,140-0002, Japan Tel: (81-3) 3450-1682 Fax: (81-3) 3474-2385

Email: fcl-contact@cs.jp.fujitsu.com Web: www.fujitsu.com/jp/fcl/

North and South America

FUJITSU COMPONENTS AMERICA, INC 2290 North First Street, Suite 212 San Jose, CA 95131, USA Tel: (1-408) 745-4900 Fax: (1-408) 745-4970

Email: components@us.fujitsu.com Web: us.fujitsu.com/components

Europe

FUJITSU COMPONENTS EUROPE B.V.

Diamantlaan 25 2132 WV Hoofddorp Netherlands Tel: (31-23) 5560910 Fax: (31-23) 5560950

Email: info@fceu.fujitsu.com Web: www.fujitsu.com/uk/components Asia Pacific

FUIITSU COMPONENTS ASIA, LTD. 102E Pasir Panjang Road #01-01 Citilink Warehouse Complex

Singapore 118529 Tel: (65) 6375-8560 Fax: (65) 6273-3021 Email: fcal@sq.fujitsu.com

Web: www.fujitsu.com/sg/products/devices/components

FUJITSU ELECTRONIC COMPONENTS (SHANGHAI) CO., LTD.

Unit 4306, InterContinental Center 100 Yu Tong Road, Shanghai 200070,

China

Tel: (86-21) 3253 0998 Fax: (86-21) 3253 0997 Email: fcal@sq.fujitsu.com

Web: www.fujitsu.com/sg/products/devices/components

FUJITSU COMPONENTS HONG KONG CO., LTD Unit 506, Inter-Continental Plaza

No.94 Granville Road, Tsim Sha Tsui, Kowloon,

Hong Kong Tel: (852) 2881-8495 Tex: (852) 2894-9512

Email: fcal@sg.fujitsu.com

Web: www.fujitsu.com/sg/products/devices/components/

Когеа

FUIITSU COMPONENTS KOREA LIMITED Alpha Tower #403, 645 Sampyeong-dong, Bundang-gu, Seongnam-si, Gyeonggi-do,

13524 Korea Tel: (82) 31-708-7108 Fax: (82) 31-709-7108 Email: fcal@sg.fujitsu.com

www.fujitsu.com/sg/products/devices/components/

©2018 Fujitsu Components Europe B.V. All rights reserved. All trademarks or registered trademarks are the property of their respective owners.

The contents, data and information in this datasheet are provided by Fujitsu Component Ltd. as a service only to its user and only for general information purposes.

The use of the contents, data and information provided in this datasheet is at the users' own risk.

Fujitsu has assembled this datasheet with care and will endeavor to keep the contents, data and information correct, accurate, comprehensive, complete and up to date.

Fujitsu Components Europe B.V. and affiliated companies do however not accept any responsibility or liability on their behalf, nor on behalf of its employees, for any loss or damage, direct, indirect or consequential, with respect to this datasheet, its contents, data, and information and related graphics and the correctness, reliability, accuracy, comprehensiveness, usefulness, availability and completeness thereof.

Nor do Fujitsu Components Europe B.V. and affiliated companies accept on their behalf, nor on behalf of its employees, any responsibility or liability for any representation or warrant of any kind, express or implied, including warranties of any kind for merchantability or fitness for particular use, with respect to these datasheets, its contents, data, information and related graphics and the correctness, reliability, accuracy, comprehensiveness, usefulness, availability and completeness thereof. Rev. August 29, 2018