

Pin Assignments

AZ78LXX

3-TERMINAL POSITIVE LINEAR REGULATOR

Description

The AZ78LXX series are three terminal positive regulators with several fixed output voltages. These regulators can provide local on card regulation, eliminating the distribution problems associated with single point regulation. The AZ78LXX can be used in logic systems, instrumentation, HiFi, and other solid state electronic equipment. When used as a Zener diode/resistor combination replacement, the AZ78LXX usually results in an effective output impedance improvement of two orders of magnitude, and lower quiescent current.

With adequate heat sinking, the AZ78LXX can deliver 100mA output current. Current limiting is included to limit the peak output current to a safe value. Thermal protection is also provided. If internal power dissipation becomes too high for the heat sinking provided, the thermal shutdown circuit takes over, preventing the IC from overheating.

The AZ78LXX are available in the plastic TO-92 (bulk or ammo packing), SOT-223 and SOT-89 packages.

Features

- Output Current up to 100mA
- Fixed Output Voltages of 5V and 9V
- Output Voltage Tolerances of ±5% over the Full Temperature Range
- Internal Short Circuit Current-limiting
- Internal Thermal Overload Protection
- No External Components
- For automotive applications requiring specific change control (i.e. parts qualified to AEC-Q100/101/200, PPAP capable, and manufactured in IATF 16949 certified facilities), please <u>contact us</u> or your local Diodes representative. <u>https://www.diodes.com/guality/product-definitions/</u>





Applications

- High Efficiency Linear Regulator
- Post Regulation for Switching Supply
- Microprocessor Power Supply
- Mother Board I/O Power Supply



Typical Applications Circuit





Absolute Maximum Ratings (Note 2)

Symbol	Parameter	Rating		Unit
VIN	Input Voltage	20	V	
TJ	Operating Junction Temperature	+150		°C
T _{LEAD}	Lead Temperature (Soldering, 10sec)	+26	°C	
PD	Power Dissipation ($T_A = +25^{\circ}C$)	TO-92	0.65	
		SOT-223	0.7	W
		SOT-89	0.65	<u> </u>
T _{STG}	Storage Temperature Range	-65 to	°C	
ESD	ESD (Human Body Model)	200	V	
ESD	ESD (Machine Model)	20	V	

Note 2: Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "Recommended Operating Conditions" is not implied. Exposure to "Absolute Maximum Ratings" for extended periods may affect device reliability.

Recommended Operating Conditions

Symbol	Parameter		Min	Мах	Unit	
V _{IN}	Input Voltage	AZ78L05	_	15		
		AZ78L09	_	18	V	
TJ	Operating Junction Temperature		-40	+125	°C	





Electrical Characteristics

AZ78L05 Electrical Characteristics (Limits in standard typeface are for T_J = +25°C, Bold typeface applies over -40°C to +125°C, I_{OUT} = 40mA, C_{IN} = 0.33 μ F, C_{OUT} = 0.1 μ F, V_{IN} = 10V, unless otherwise specified.)

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
	Output Voltage	_	4.8	5	5.2	
V _{OUT}		7.0V ≤ V _{IN} ≤ 15V 1.0mA ≤ I _{OUT} ≤ 40mA (Note 3)	4.75	_	5.25	V
V _{RLINE}	Line Regulation	$7.0V \le V_{IN} \le 15V$	—	18	75	mV
Vrload	Load Regulation	1.0mA ≤ I _{OUT} ≤ 100mA	_	20	60	mV
VDROP	Dropout Voltage	—		1.6	—	V
I _{LIMIT}	Current Limit	T _J = +25°C		150		mA
IQ	Quiescent Current	I _{OUT} = 0	_	3	5	mA
ΔlQ	Quiescent Current Change	8.0V ≤ V _{IN} ≤ 15V		_	1.0	
		1.0mA ≤ I _{OUT} ≤ 40mA	_	_	0.1	mA
No	Output Noise Voltage	10Hz ≤ f ≤ 100kHz (Note 4)	_	40	_	μV
PSRR	Ripple Rejection	f = 120Hz, 8.0V ≤ V _{IN} ≤ 15V	47	62		dB
I _{PK}	Peak Output Current		-	150		mA
$\Delta V_{OUT} / \Delta T$	Average Temperature Coefficient of Output Voltage	I _{OUT} = 5.0mA	_	0.65	_	mV/°C
V _{IN} (Min)	Minimum Value of Input Voltage Required to Maintain Line Regulation		_	6.7	7	V
		TO-92	_	81	_	
θυς	Thermal Resistance	SOT-89	_	29.8	_	°C/W
		SOT-223	_	71	_	

Notes:

Power Dissipation ≤ 0.6W.
Recommended minimum load capacitance of 0.01µF to limit high frequency noise.



Electrical Characteristics (continued)

AZ78L09 Electrical Characteristics (Limits in standard typeface are for T_J = +25°C, Bold typeface applies over -40°C to +125°C, I_{OUT} = 40mA, C_{IN} = 0.33 μ F, C_{OUT} = 0.1 μ F, V_{IN} = 15V, unless otherwise specified.)

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
	Output Voltage	-	8.6	9	9.4	
V _{OUT}		12V ≤ V _{IN} ≤ 18V 1.0mA ≤ I _{OUT} ≤ 40mA (Note 3)	8.55	Ι	9.45	V
V _{RLINE}	Line Regulation	$12V \le V_{IN} \le 18V$	—	18	75	mV
V _{RLOAD}	Load Regulation	1.0mA ≤ I _{OUT} ≤ 100mA	_	20	90	mV
VDROP	Dropout Voltage	_		1.6	—	V
I _{LIMIT}	Current Limit	T _J = +25°C		150		mA
Ι _Q	Quiescent Current	I _{OUT} = 0		3	5	mA
Δl _Q	Quiescent Current Change	12V ≤ V _{IN} ≤ 18V		_	1.5	
		1.0mA ≤ I _{OUT} ≤ 40mA	_	-	0.1	mA
No	Output Noise Voltage	10Hz ≤ f ≤ 100kHz (Note 4)	_	70	_	μV
PSRR	Ripple Rejection	f = 120Hz, 12V ≤ V _{IN} ≤ 18V	38	44	_	dB
I _{PK}	Peak Output Current		-	150	—	mA
$\Delta V_{OUT} / \Delta T$	Average Temperature Coefficient of Output Voltage	I _{OUT} = 5.0mA	_	0.9	_	mV/°C
V _{IN} (Min)	Minimum Value of Input Voltage Required to Maintain Line Regulation		_	10.7	_	V
		TO-92	_	81	_	
οιθ	Thermal Resistance	SOT-89	_	84	_	°C/W
		SOT-223	—	71	—	

Notes:

Power Dissipation ≤ 0.6W.
Recommended minimum load capacitance of 0.01µF to limit high frequency noise.



Performance Characteristics



Quiescent Current vs. Junction Temperature



Line Transient Response (Conditions: VIN=10 to 11V, VOUT=5V, IOUT=40mA)





Dropout Voltage vs. Junction Temperature



Input Bias Current vs. Input Voltage



Load Transient Response (Conditions: VIN=10V, VOUT=5V, IOUT=1 to 50mA)



OLETE – PART DISCONTINUED



Ordering Information





Package Outline Dimensions (All dimensions in mm(inch).)

Please see http://www.diodes.com/package-outlines.html for the latest version.

(1) Package Type: TO-92 (Bulk Packing)





Package Outline Dimensions (continued) (All dimensions in mm(inch).)

Please see http://www.diodes.com/package-outlines.html for the latest version.

(2) Package Type: TO-92 (Ammo Packing)





Package Outline Dimensions (continued) (All dimensions in mm(inch).)

Please see http://www.diodes.com/package-outlines.html for the latest version.

(3) Package Type: SOT-223





Package Outline Dimensions (continued) (All dimensions in mm(inch).)

Please see http://www.diodes.com/package-outlines.html for the latest version.

(4) Package Type: SOT-89





IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2020, Diodes Incorporated

www.diodes.com