

Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild guestions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer



November 2007

KSD882 NPN Epitaxial Silicon Transistor

Recommended Applications

• Audio Frequency Power Amplifier

Featuers

- Low Speed Switcing
- Complement to KSB772.



Absolute Maximum Ratings* T_a = 25°C unless otherwise noted

Symbol	Parameter	Ratings	Units	
BV _{CBO}	Collector-Base Voltage	40	٧	
BV _{CEO}	Collector-Emitter Voltage	30	V	
BV _{EBO}	Emitter-Base Voltage	5	V	
I _C	Collector Current(DC)	3	А	
I _C	Collector Current(Pulse)**	7	Α	
I _B	Base Current	0.6	А	
P _D	Total Device Dissipation(T _C =25°C) Total Device Dissipation(T _a =25°C)	10 1	W W	
T _J , T _{STG}	Junction and Storage Temperature	- 55 ~ +150	°C	

^{*} These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

Electrical Characteristics. T_a=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
BV _{CBO}	Collector-Base Breakdown Voltage	I _C =500uA, I _E =0	40			V
BV _{CEO}	Collector-Emitter Breakdown Voltage	I _C =5mA, I _B =0	30			V
BV _{EBO}	Emitter-Base Breakdown Voltage	I _E =500uA, I _C =0	5			V
I _{CBO}	Collector Cut-off Current	V _{CB} = 30V, I _E = 0			1	μА
I _{EBO}	Emitter Cut-off Current	$V_{EB} = 3V, I_{C} = 0$			1	μА
h _{FE1} h _{FE2}	*DC Current Gain	$V_{CE} = 2V$, $I_C = 20$ mA $V_{CE} = 2V$, $I_C = 1$ A	30 60	150 160	400	
V _{CE} (sat)	*Collector-Emitter Saturation Voltage	$I_C = 2A, I_B = 0.2A$		0.3	0.5	V
V _{BE} (sat)	*Base-Emitter Saturation Voltage	$I_C = 2A, I_B = 0.2A$		1.0	2.0	V
f _T	Current Gain Bandwidth Product	$V_{CE} = 5V, I_{E} = 0.1A$		90		MHz
C _{ob}	Output Capacitance	V _{CB} = 10V, I _E = 0 f = 1MHz		45		pF

 $^{^{\}star}~$ Pulse Test: PW≤350 $\mu s,$ Duty Cycle≤2% Pulsed

© 2007 Fairchild Semiconductor Corporation

KSD882 Rev. B

www.fairchildsemi.com

^{**} PW≤10ms, Duty Cycle≤50%

h_{FE} Classification

Classification	R	0	Y	G
h _{FE2}	60 ~ 120	100 ~ 200	160 ~ 320	200 ~ 400

Ordering Information

Part Number	Marking	Package	Packing Method	Remarks
KSD882OSTU	D882O	TO-126	TUBE	hFE1 R grade
KSD882RSTU	D882R	TO-126	TUBE	hFE1 O grade
KSD882YSTU	D882Y	TO-126	TUBE	hFE1 Y grade
KSD882GSTU	D882G	TO-126	TUBE	hFE1 G grade

^{* 1.} Affix "-S-" means the standard TO126 Package. If the affix is "-STS-" instead of "-S-", that means the short-lead TO126 package.

2. Suffix "-TU" means the tube packing, The Suffix "TU" could be replaced to other suffix character as packing method.

Typical Characteristics




Figure 1. Static Characteristic




Figure 2. DC current Gain




Figure 3. Base-Emitter Saturation Voltage Collector-Emitter Saturation Voltage




Figure 4. Current Gain Bandwidth Product




Figure 5. Collector Output Capacitance




Figure 6. Safe Operating Area

Typical Characteristics




Figure 7. Derating Curve Of Safe Operating Areas




Figure 8. Power Derating





TRADEMARKS

The following are registered and unregistered trademarks and service marks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx® Power247® Green FPS™ SuperSOT™-8 POWEREDGE® Build it Now™ Green FPS™ e-Series™ SyncFET™ GTO™ The Power Franchise® CorePLUS™ Power-SPM™ i-Lo™ $\mathsf{PowerTrench}^{\circledR}$ $CROSSVOLT^{TM}$ power CTL™ IntelliMAX™ Programmable Active Droop™ ISOPLANAR™ **QFET®** TinyBoost™ Current Transfer Logic™ EcoSPARK[®] QSTM MegaBuck™ TinyBuck™ TinyLogic[®] MICROCOUPLER™ QT Optoelectronics™ Fairchild[®] **TINYOPTO™** MicroFET™ Quiet Series™ Fairchild Semiconductor® MicroPak™ RapidConfigure™ TinyPower™ FACT Quiet Series™ Motion-SPM™ SMART START™ TinyPWM™ FACT[®] OPTOLOGIC® SPM[®] TinyWire™ $\mathsf{FAST}^{\mathbb{R}}$ OPTOPLANAR® STEALTH™ µSerDes™ UHC® FastvCore™ SuperFET™ FPS™ PDP-SPM™ SuperSOT™-3 UniFET™ FRFET® Power220® SuperSOT™-6 VCX^{TM} Global Power ResourceSM

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. I30

© 2007 Fairchild Semiconductor Corporation

www.fairchildsemi.com

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hol

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative