

LM78TXX


3-Terminal 3A Positive Voltage Regulator

Features


- Output Current in Excess of 3.0A
- Output Transistor Safe Operating Area Compensation
- Power Dissipation :25W
- Internal Short Circuit Current Limiting
- Internal Thermal Overload Protection
- Output Voltage Offered in 4% Tolerance
- No External Components Required
- Output Voltage of 5,12 and 15V

Description

This family of fixed voltage regulators are monolithic integrated circuit capable of driving loads in excess of 3.0 A.



Internal Block Diagram



Absolute Maximum Ratings

Parameter	Symbol	Value	Unit
Input Voltage (for VO = 5V to 12V) (for VO = 15V)	VI	35 40	V V
Power Dissipation	PD	Internally limited	
Thermal Resistance, Junction to Air (Note1, 2) Ta = +25°C	RθJA	65	°C/W
Thermal Resistance, Junction to Case (Note1) Tc = +25°C	RθJC	2.5	°C/W
Operating Junction Temperature Range	TJ	0 ~ +125	°C
Storage Temperature Range	TSTG	-65 ~ +150	°C

Note:

- Thermal resistance test board Size: 76.2mm * 114.3mm * 1.6mm(1S0P) JEDEC standard: JESD51-3, JESD51-7
- 2. Assume no ambient airflow.

Electrical Characteristics(LM78T05)

(VI = 10V, IO = 3.0 A, $0^{\circ}C \le T_J \le +125^{\circ}C$, Po $\le P_{MAX}$ (Note3), unless otherwise specified.)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit
Output Voltage	Vo	$5\text{mA} \le \text{lo} \le 3.0\text{A}$, $T_J = +25^{\circ}\text{C}$ $7.3\text{V} \le \text{VI} \le 20\text{V}$, $5\text{mA} \le \text{lo} \le 2.0\text{A}$	4.8 4.75	5.0 5.0	5.2 5.25	V
Line Regulation (Note4)	ΔVο	$7.2V \le VI \le 35V$, $Io=5mA$, $TJ=+25^{\circ}C$ $7.2V \le VI \le 35V$, $Io=1.0A$, $TJ=+25^{\circ}C$ $7.5V \le VI \le 20V$, $Io=2.0A$, $TJ=+25^{\circ}C$ $8.0V \le VI \le 12V$, $Io=3.0A$, $TJ=+25^{\circ}C$	-	3.0	25	mV
Load Regulation (Note4)	ΔVΟ	$5\text{mA} \le \text{lo} \le 3.0\text{A}$, TJ = +25°C $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	10 15	30 80	mV mV
Thermal Regulation	REGT	Pulse =10ms, P = 20W T _A = +25°C	-	0.002	0.03	%Vo/W
Quiescent Current	IQ	$5\text{mA} \le \text{lo} \le 3.0\text{A}$, $T_J = +25^{\circ}\text{C}$ $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	3.5 4.0	5.0 6.0	mA mA
Quiescent Current Change	ΔlQ	$7.2V \le VI \le 35V$, $Io = 5mA$ $T_J = +25^{\circ}C$; $7.5V \le VI \le 20V$, $Io = 2.0A$; $5mA \le Io \le 3.0A$, $T_J = +25^{\circ}C$	-	0.1	0.8	mA
Ripple Rejection	RR	$f = 120Hz, 8V \le V_I \le 18V, I_0 = 2.0A$ $T_J = +25^{\circ}C$	-	75	-	dB
Dropout Voltage	VD	Io = 3A ,TJ = +25°C	-	2.2	2.5	V
Output Noise Voltage	VN	$T_A = +25^{\circ}C$, $10Hz \le f \le 100kHz$	-	10	1	μV/Vo
Peak Output Current	IPK	T _A = +25°C	-	5.0	-	Α
Output Resistance	Ro	f = 1.0kHz	-	2.0	-	mΩ
Short Circuit Current Limit	Isc	VI = 35V, T _J =+25°C	-	1.5	2.5	Α
Average Temperature Coefficient of Output Voltage	ΔV0/ΔΤ	Io = 5.0mA	-	0.2	-	mV/°C

- 3. Although power dissipation is internally limited, specifications apply only for Po ≤ Pmax, Pmax = 25W
- 4. Load and line regulation are specified at constant junction temperature. Change in Vo due heating effects must be taken into account separately. Pulse testing with low duty is used.

Electrical Characteristics(LM78T12) (Continued)

(VI = 19V, IO = 3.0 A, 0° C \leq TJ \leq +125 $^{\circ}$ C, Po \leq PMAX (Note1), unless otherwise specified.)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit
Output Voltage	Vo	$5\text{mA} \le \text{lo} \le 3.0\text{A}$, $T_J = +25^{\circ}\text{C}$ $14.5\text{V} \le \text{VI} \le 27\text{V}$, $5\text{mA} \le \text{lo} \le 2.0\text{A}$	11.5 11.4	12 12	12.5 12.8	V
Line Regulation (Note2)	ΔVο	$\begin{array}{l} 14.5 V \leq VI \leq 35 V, \ lo=5 mA, \ T_J = +25 ^{\circ} C \\ 14.5 V \leq VI \leq 35 V, \ lo=1.0 A, \ T_J = +25 ^{\circ} C \\ 14.9 V \leq VI \leq 28 V, \ lo = 2.0 A, \ T_J = +25 ^{\circ} C \\ 16 V \leq VI \leq 22 V, \ lo = 3.0 A, \ T_J = +25 ^{\circ} C \end{array}$		6.0	45	mV
Load Regulation (Note2)	ΔVο	$5\text{mA} \le \text{lo} \le 3.0\text{A}, \text{TJ} = +25^{\circ}\text{C}$ $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	10 15	30 80	mV mV
Thermal Regulation	REGT	Pulse =10ms, P = 20W T _A = +25°C	-	0.002	0.03	%Vo/W
Quiescent Current	IQ	$5\text{mA} \le \text{lo} \le 3.0\text{A}, \text{TJ} = +25^{\circ}\text{C}$ $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	3.5 4.0	5.0 6.0	mA mA
Quiescent Current Change	ΔlQ	$14.5V \le VI \le 35V$, $Io = 5mA$ $TJ = +25^{\circ}C$; $14.9V \le VI \le 27V$, $Io = 2.0A$; $5mA \le Io \le 3.0A$, $TJ = +25^{\circ}C$	-	0.1	0.8	mA
Ripple Rejection	RR	$f = 120Hz, 15V \le V_I \le 25V, Io = 2.0A$ $T_J = +25$ °C	-	67	-	dB
Dropout Voltage	VD	lo = 3A,TJ =+25°C	-	2.2	2.5	V
Output Noise Voltage	VN	TA =+25°C, $10Hz \le f \le 100kHz$	-	10	-	μV/Vo
Peak Output Current	IPK	T _A =+25°C	-	5.0	-	Α
Output Resistance	Ro	f = 1.0kHz	•	2.0	ı	mΩ
Short Circuit Current Limit	Isc	VI = 35V, TJ =+25°C		1.5	2.5	Α
Average Temperature Coefficient of Output Voltage	ΔV0/ΔΤ	Io = 5.0mA	-	0.5	-	mV/°C

- 1. Although power dissipation is internally limited, specifications apply only for $P_0 \le P_0 \le$
- 2. Load and line regulation are specified at constant junction temperature. Change in Vo due heating effects must be taken into account separately. Pulse testing with low duty is used. (PMAX = 25W)

Electrical Characteristics(LM78T15) (Continued)


(VI = 23V, IO = 3.0 A, 0° C \leq TJ \leq +125 $^{\circ}$ C, Po \leq PMAX (Note1), unless otherwise specified.)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit
Output Voltage	Vo	$5mA \le lo \le 3.0A$, $T_J = +25^{\circ}C$ $17.5V \le VI \le 30V$, $5mA \le lo \le 2.0A$		15 15	15.6 15.75	V
Line Regulation (Note2)	ΔVο	$\begin{array}{l} 17.6V \leq VI \leq 40V, \ lo=5mA, \ T_J=+25^{\circ}C \\ 17.6V \leq VI \leq 40V, \ lo=1.0A, \ T_J=+25^{\circ}C \\ 18V \leq VI \leq 30V, \ lo=2.0A, \ T_J=+25^{\circ}C \\ 20V \leq VI \leq 26V, \ lo=3.0A, \ T_J=+25^{\circ}C \end{array}$		7.5	55	mV
Load Regulation (Note2)	ΔVο	$5\text{mA} \le \text{lo} \le 3.0\text{A}, \text{TJ} = +25^{\circ}\text{C}$ $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	10 15	30 80	mV mV
Thermal Regulation	REGT	Pulse =10ms, P = 20W T _A = +25°C	-	0.002	0.03	%Vo/W
Quiescent Current	IQ	$5\text{mA} \le \text{lo} \le 3.0\text{A}, \text{T}_J = +25^{\circ}\text{C}$ $5\text{mA} \le \text{lo} \le 3.0\text{A}$	-	3.5 4.0	5.0 6.0	mA mA
Quiescent Current Change	ΔlQ	17.6V \leq VI \leq 40V, Io = 5mA TJ =+25°C; 18V \leq VI \leq 30V, Io =2.0A; 5mA \leq Io \leq 3.0A, TJ =+25°C	-	0.1	0.8	mA
Ripple Rejection	RR	$\begin{array}{l} f = 120 Hz, \ 18.5 V \leq V_I \leq 28.5 V, \ Io = 2.0 A \\ T_J = +25 ^{\circ} C \end{array}$	-	65	-	dB
Dropout Voltage	VD	$Io = 3A$, $T_J = +25^{\circ}C$	-	2.2	2.5	V
Output Noise Voltage	VN	$T_A = +25^{\circ}C$, $10Hz \le f \le 100kHz$	-	10	-	μV/Vo
Peak Output Current	IPK	T _A = +25°C	-	5.0	-	Α
Output Resistance	Ro	f = 1.0kHz	-	2.0	-	mΩ
Short Circuit Current Limit	Isc	VI = 40V, TJ = +25°C	-	1.0	2.0	Α
Average Temperature Coefficient of Output Voltage	ΔV0/ΔΤ	Io = 5.0mA	-	0.5	-	mV/°C

^{1.} Although power dissipation is internally limited, specifications apply only for $P_0 \le P_0 \le$

^{2.} Load and line regulation are specified at constant junction temperature. Change in Vo due heating effects must be taken into account separately. Pulse testing with low duty is used. (PMAX = 25W)

Typical Application




- 1. To specify an output voltage, substitute voltage value for "XX".
- 2. Bypass Capacitors are recommend for optimum stability and transient response and should be located as close as possible to the regulator

Mechanical Dimensions

Package

Dimensions in millimeters

TO-220 [SINGLE GAUGE]



Ordering Information

Product Number	Package	Operating Temperature
LM78T05CT		
LM78T12CT	TO-220	0 ~ +125°C
LM78T15CT		

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com