

## Is Now Part of



## ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo



October 1987 Revised March 2002

## CD4013BC Dual D-Type Flip-Flop

## **General Description**

The CD4013B dual D-type flip-flop is a monolithic complementary MOS (CMOS) integrated circuit constructed with N- and P-channel enhancement mode transistors. Each flip-flop has independent data, set, reset, and clock inputs and "Q" and "Q" outputs. These devices can be used for shift register applications, and by connecting "Q" output to the data input, for counter and toggle applications. The logic level present at the "D" input is transferred to the Q output during the positive-going transition of the clock pulse. Setting or resetting is independent of the clock and is accomplished by a high level on the set or reset line respectively.

#### **Features**

■ Wide supply voltage range: 3.0V to 15V■ High noise immunity: 0.45 V<sub>DD</sub> (typ.)

■ Low power TTL: fan out of 2 driving 74L compatibility: or 1 driving 74LS

## **Applications**


- Automotive
- Data terminals
- Instrumentation
- Medical electronics
- · Alarm system
- · Industrial electronics
- · Remote metering
- Computers

## **Ordering Code:**

Order Number	Package Number	Package Description
CD4013BCM	M14A	14-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150" Narrow
CD4013BCSJ	M14D	14-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
CD4013BCN	N14A	14-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide

Devices also available in Tape and Reel. Specify by appending the suffix letter "X" to the ordering code.

### **Connection Diagram**



### **Truth Table**

CL (Note 1)	D	R	S	Q	Q
~	0	0	0	0	1
~	1	0	0	1	0
~	х	0	0	Q	Q
х	х	1	0	0	1
х	х	0	1	1	0
х	х	1	1	1	1

No Change x = Don't Care Case

Note 1: Level Change

© 2002 Fairchild Semiconductor Corporation

DS005946

## Absolute Maximum Ratings(Note 2)

(Note 3)

DC Supply Voltage (V<sub>DD</sub>)  $-0.5 \text{ V}_{DC} \text{ to } +18 \text{ V}_{DC}$  Input Voltage (V<sub>IN</sub>)  $-0.5 \text{ V}_{DC} \text{ to } V_{DD} +0.5 \text{ V}_{DC}$  Storage Temperature Range (T<sub>S</sub>)  $-65^{\circ}\text{C to } +150^{\circ}\text{C}$ 

Power Dissipation (P<sub>D</sub>)

Dual-In-Line 700 mW Small Outline 500 mW

Lead Temperature (T<sub>L</sub>)

(Soldering, 10 seconds) 260°C

# Recommended Operating Conditions (Note 3)

DC Supply Voltage ( $V_{DD}$ ) +3  $V_{DC}$  to +15  $V_{DC}$  Input Voltage ( $V_{IN}$ ) 0  $V_{DC}$  to  $V_{DD}$   $V_{DC}$  Operating Temperature Range ( $T_A$ ) -55°C to +125°C

Note 2: "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed, they are not meant to imply that the devices should be operated at these limits. The tables of "Recommended Operating Conditions" and "Electrical Characteristics" provide conditions for actual device operation.

Note 3:  $V_{SS} = 0V$  unless otherwise specified.

## DC Electrical Characteristics (Note 3)

Symbol	Parameter	Conditions	–55°C		+25°C			+125°C		Units
Syllibol	Farameter	Conditions	Min	Max	Min	Тур	Max	Min	Max	Units
I <sub>DD</sub>	Quiescent Device	$V_{DD} = 5V$ , $V_{IN} = V_{DD}$ or $V_{SS}$		1.0			1.0		30	
	Current	$V_{DD} = 10V$ , $V_{IN} = V_{DD}$ or $V_{SS}$		2.0			2.0		60	μΑ
		$V_{DD} = 15V$ , $V_{IN} = V_{DD}$ or $V_{SS}$		4.0			4.0		120	
V <sub>OL</sub>	LOW Level	I <sub>O</sub>   < 1.0 μA								
	Output Voltage	$V_{DD} = 5V$		0.05			0.05		0.05	V
		$V_{DD} = 10V$		0.05			0.05		0.05	V
		$V_{DD} = 15V$		0.05			0.05		0.05	
V <sub>OH</sub>	HIGH Level	I <sub>O</sub>   < 1.0 μA								
	Output Voltage	$V_{DD} = 5V$	4.95		4.95			4.95		V
		$V_{DD} = 10V$	9.95		9.95			9.95		V
		$V_{DD} = 15V$	14.95		14.95			14.95		
V <sub>IL</sub>	LOW Level	I <sub>O</sub>   < 1.0 μA								
	Input Voltage	$V_{DD} = 5V$ , $V_{O} = 0.5V$ or 4.5V		1.5			1.5		1.5	V
		$V_{DD} = 10V, V_{O} = 1.0V \text{ or } 9.0V$		3.0			3.0		3.0	v
		$V_{DD} = 15V$ , $V_{O} = 1.5V$ or $13.5V$		4.0			4.0		4.0	
V <sub>IH</sub>	HIGH Level	I <sub>O</sub>   < 1.0 μA								
	Input Voltage	$V_{DD} = 5V, V_{O} = 0.5V \text{ or } 4.5V$	3.5		3.5			3.5		V
		$V_{DD} = 10V, V_{O} = 1.0V \text{ or } 9.0V$	7.0		7.0			7.0		v
		$V_{DD} = 15V$ , $V_{O} = 1.5V$ or $13.5V$	11.0		11.0			11.0		
I <sub>OL</sub>	LOW Level Output	$V_{DD} = 5V, V_{O} = 0.4V$	0.64		0.51	0.88		0.36		
	Current (Note 4)	$V_{DD} = 10V, V_{O} = 0.5V$	1.6		1.3	2.25		0.9		mA
		$V_{DD} = 15V, V_{O} = 1.5V$	4.2		3.4	8.8		2.4		
I <sub>OH</sub>	HIGH Level Output	$V_{DD} = 5V, V_{O} = 4.6V$	-0.64		-0.51	-0.88		-0.36		
	Current (Note 4)	$V_{DD} = 10V, V_{O} = 9.5V$	-1.6		-1.3	-2.25		-0.9		mA
		$V_{DD} = 15V, V_{O} = 13.5V$	-4.2		-3.4	-8.8		-2.4		
I <sub>IN</sub>	Input Current	$V_{DD} = 15V, V_{IN} = 0V$		-0.1		-10 <sup>-5</sup>	-0.1		-1.0	
		$V_{DD} = 15V, V_{IN} = 15V$		0.1		10 <sup>-5</sup>	0.1		1.0	μА


Note 4: I<sub>OH</sub> and I<sub>OL</sub> are measured one output at a time.


# AC Electrical Characteristics (Note 5) $T_A = 25^{\circ}C$ , $C_L = 50$ pF, $R_L = 200$ k, unless otherwise noted


Symbol	Parameter	Conditions	Min	Тур	Max	Units
CLOCK OPERAT	TION		ı		l l	
t <sub>PHL</sub> , t <sub>PLH</sub>	Propagation Delay Time	$V_{DD} = 5V$		200	350	
		$V_{DD} = 10V$		80	160	ns
		$V_{DD} = 15V$		65	120	
t <sub>THL</sub> , t <sub>TLH</sub>	Transition Time	$V_{DD} = 5V$		100	200	
		$V_{DD} = 10V$		50	100	ns
		$V_{DD} = 15V$		40	80	
w <sub>L</sub> , t <sub>wH</sub>	Minimum Clock	$V_{DD} = 5V$		100	200	
	Pulse Width	$V_{DD} = 10V$		40	80	ns
		$V_{DD} = 15V$		32	65	
RCL, tFCL	Maximum Clock Rise and	$V_{DD} = 5V$			15	
	Fall Time	$V_{DD} = 10V$			10	μs
		$V_{DD} = 15V$			5	
t <sub>su</sub>	Minimum Set-Up Time	$V_{DD} = 5V$		20	40	
		$V_{DD} = 10V$		15	30	ns
		$V_{DD} = 15V$		12	25	
CL	Maximum Clock	$V_{DD} = 5V$	2.5	5		
	Frequency	$V_{DD} = 10V$	6.2	12.5		MHz
		$V_{DD} = 15V$	7.6	15.5		
SET AND RESET	OPERATION	•				
PHL(R),	Propagation Delay Time	$V_{DD} = 5V$		150	300	
PLH(S)		$V_{DD} = 10V$		65	130	ns
		$V_{DD} = 15V$		45	90	
WH(R),	Minimum Set and	$V_{DD} = 5V$		90	180	
WH(S)	Reset Pulse Width	$V_{DD} = 10V$		40	80	ns
		$V_{DD} = 15V$		25	50	
C <sub>IN</sub>	Average Input Capacitance	Any Input		5	7.5	pF

Note 5: AC Parameters are guaranteed by DC correlated testing.

## **Switching Time Waveforms**







#### Physical Dimensions inches (millimeters) unless otherwise noted (Continued) 0.740 - 0.770(18.80 - 19.56)0.090 (2.286) 14 13 12 14 13 12 11 10 9 8 0.250 ± 0.010 (6.350 ± 0.254) PIN NO. 1 IDENT PIN NO. 1 IDENT 1 2 3 4 5 6 7 1 2 3 $\frac{0.092}{(2.337)}$ DIA 0.030 MAX (0.762) DEPTH OPTION 1 OPTION 02 $\frac{0.135 \pm 0.005}{(3.429 \pm 0.127)}$ 0.300 - 0.320 $\overline{(7.620 - 8.128)}$ $\frac{0.145 - 0.200}{(3.683 - 5.080)}$ 0.065 0.00 4° TYP OPTIONAL (1.651)95° ±5° $\frac{0.008 - 0.016}{(0.203 - 0.406)}$ TYP 0.020 (0.508)0.125 - 0.150 $\overline{(3.175 - 3.810)}$ 0.280

14-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide Package Number N14A

 $\frac{0.050\pm0.010}{(1.270-0.254)}$  TYP

 $\frac{0.100 \pm 0.010}{(2.540 \pm 0.254)} \text{ TYP}$ 

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications.

#### LIFE SUPPORT POLICY

0.014-0.023 TYP

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

(7.112) MIN

 $0.325 { +0.040 \atop -0.015 \atop -0.015 \atop \hline (8.255 { +1.016 \atop -0.381 \atop }$ 

N14A (REV F)

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hol

#### **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Phone: 421 33 790 2910

Japan Customer Focus Center

Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

www.onsemi.com