



NCP508SQ15T1GEVB: 1.5 V WDFN Evaluation Board

The NCP508 is a 50 mA low noise voltage regulator, designed to exhibit fast turn on time and high ripple rejection. Each device contains a voltage reference unit, an error amplifier, a PMOS power transistor, resistors for setting output voltage, current limit, and temperature limit protection circuits.



Features and Applications

Features

- Very Low Noise at 39 Vrms without a Bypass Capacitor
- High Ripple Rejection of 70 dB at 1 kHz
- High Ripple Rejection of 70 dB at 1 kHz

Evaluation/Development Tool Information

Product	Status	Compliance	Short Description	Parts Used	Action
NCP508SQ15T1GEVB	Active	Pb-free	1.5 V WDFN Evaluation Board	NCP508SQ15T1G	Contact Local Sales Office

Technical Documents

Type	Document Title	Document ID/Size	Rev
Eval Board: BOM	NCP508SQ15T1GEVB Bill of Materials ROHS Compliant	NCP508SQ15T1GEVB_BOM_ROHS.PDF - 114.0 KB	0
Eval Board: Gerber	NCP508SQ15T1GEVB Gerber Layout Files (Zip Format)	NCP508SQ15T1GEVB_GERBER.ZIP - 21.0 KB	0
Eval Board: Schematic	NCP508SQ15T1GEVB Schematic	NCP508SQ15T1GEVB_SCHEMATIC.PDF - 44.0 KB	0
Eval Board: Test Procedure	NCP508SQ15T1GEVB Test Procedure	NCP508SQ15T1GEVB_TEST_PROCEDURE.PDF - 89.0 KB	0
Video	1.5 V WDFN Evaluation Board - NCP508SQ15T1GEVB	WVD17680/D	

Previously Viewed Products

Select Product... [Clear List](#)

Design Support

- [Technical Documentation](#)
- [Design Resources & Documents](#)
- [Technical Support](#)
- [Sales Support](#)

Featured Video

1.5 V WDFN Evaluation Board - NCP508SQ15T1GEVB



[More Videos ...](#)

