



PCIe 2.0 Clock Generator with 2 HCSL Outputs

### **Features**

- → PCIe<sup>®</sup> 2.0 compliant
  - Phase jitter 2.1ps RMS (typ)
- → LVDS compatible outputs
- → Supply voltage of 3.3V ±10%
- → 25MHz crystal or clock input frequency
- → HCSL outputs, 0.8V Current mode differential pair
- → Jitter 35ps cycle-to-cycle (typ)
- $\rightarrow$  Spread of -0.5%, -0.75%, and no spread
- → Industrial temperature range
- → Spread Bypass option available
- → Spread and frequency selection via external pins
- → Packaging: (Pb-free and Green)
  - 16-pin TSSOP (L16)
  - 16-pin QSOP (Q16)

### **Block Diagram**



### Description

The PI6C557-03A is a spread spectrum clock generator compliant to PCI Express<sup>®</sup> 2.0 and Ethernet requirements. The device is used for PC or embedded systems to substantially reduce Electromagnetic Interference (EMI).

The PI6C557-03A provides two differential (HCSL) or LVDS spread spectrum outputs. The PI6C557-03A is configured to select spread and clock selection. Using Pericom's patented Phase-Locked Loop (PLL) techniques, the device takes a 25MHz crystal input and produces two pairs of differential outputs (HCSL) at 25MHz, 100MHz, 125MHz and 200MHz clock frequencies. It also provides spread selection of -0.5%, -0.75%, and no spread.

### Pin Configuration (16-Pin TSSOP)







### **Pin Description**

Pin #	Pin Name	I/O Type	Description
1	S0	Input	Select pin 0 (Internal pull-up resistor). See Table 1.
2	S1	Input	Select pin 1 (Internal pull-up resistor). See Table 1.
3	SS0	Input	Spread Select pin 0 (Internal pull-up resistor). See Table 2.
4	X1/CLK	Input	Crystal or clock input. Connect to a 25MHz crystal or single ended clock.
5	X2	Output	Crystal connection. Leave unconnected for clock input.
6	OE	Input	Output enable. Internal pull-up resistor.
7	GNDX	Power	Crystal ground pin.
8	SS1	Input	Spread Select pin 1 (Internal pull-up resistor). See Table 2.
9	IREF	Output	Precision resistor attached to this pin is connected to the internal current reference.
10	CLK1	Output	HCSL compliment clock output
11	CLK1	Output	HCSL clock output
12	VDDA	Power	Connect to a +3.3V source.
13	GNDA	Power	Output and analog circuit ground.
14	CLK0	Output	HCSL compliment clock output
15	CLK0	Output	HCSL clock output
16	VDDX	Power	Connect to a +3.3V source.

#### **Table 1: Output Frequency Select Table**

S1	<b>S0</b>	CLK(MHz)
0	0	25
0	1	100
1	0	125
1	1	200

#### **Table 2: Spread Selection Table**

SS1	SS0	Spread
0	0	No Spread
0	1	Down -0.5
1	0	Down -0.75
1	1	No Spread





### **Application Information**

#### **Decoupling Capacitors**

Decoupling capacitors of 0.01µF should be connected between each V<sub>DD</sub> pin and the ground plane and placed as close to the V<sub>DD</sub> pin as possible.

#### Crystal

Use a 25MHz fundamental mode parallel resonant crystal with less than 300PPM of error across temperature.

#### **Crystal Capacitors**

C<sub>L</sub> = Crystals's load capacitance in pF

Crystal Capacitors (pF) =  $(C_L - 8) * 2$ 

For example, for a crystal with 16pF load caps, the external effective crystal cap would be 16 pF. (16-8)\*2=16.

#### Current Source (IREF) Reference Resistor - R<sub>R</sub>

If board target trace impedance is  $50\Omega$ , then  $R_R = 475\Omega$  providing an IREF of 2.32 mA. The output current (I<sub>OH</sub>) is 6\*IREF.

#### **Output Termination**

The PCI Express differential clock outputs of the PI6C557-03A are open source drivers and require an external series resistor and a resistor to ground. These resistor values and their allowable locations are shown in detail in the PCI Express Layout Guidelines section.

The PI6C557-03A can be configured for LVDS compatible voltage levels. See the LVDS Compatible Layout Guidelines section.

### **Output Structures**







### **PCI Express Layout Guidelines**

Common Recommendations for Differential Routing	Dimension or Value	Unit
L1 length, route as non-coupled $50\Omega$ trace.	0.5 max	inch
L2 length, route as non-coupled $50\Omega$ trace.	0.2 max	inch
L3 length, route as non-coupled $50\Omega$ trace.	0.2 max	inch
R <sub>S</sub>	33	Ω
R <sub>T</sub>	49.9	Ω

Differential Routing on a Single PCB	Dimension or Value	Unit
L4 length, route as coupled microstrip $100\Omega$ differential trace.	2 min to 16 max	inch
L4 length, route as coupled stripline $100\Omega$ differential trace.	1.8 min to 14.4 max	inch

Differential Routing to a PCI Express connector	Dimension or Value	Unit
L4 length, route as coupled microstrip $100\Omega$ differential trace.	0.25 min to 14 max	inch
L4 length, route as coupled stripline $100\Omega$ differential trace.	0.225 min to 12.6 max	inch

### **PCI Express Device Routing**



# **Typical PCI Express (HCSL) Waveform**







# **Application Information**

LVDS Recommendations for Differential Routing	Dimension or Value	Unit
L1 length, route as non-coupled 50 $\Omega$ trace.	0.5 max	inch
L2 length, route as non-coupled 50 $\Omega$ trace.	0.2 max	inch
RP	100	Ω
RQ	100	Ω
RT	150	Ω
L3 length, route as $100\Omega$ differential trace.		
L3 length, route as $100\Omega$ differential trace.		

# **LVDS Device Routing**





Note:



PI6C557-03A

### **Maximum Ratings**

(Above which useful life may be impaired. For user guidelines, not tested.)

Supply Voltage to Ground Potential 5.5V
All Inputs and Outputs
Ambient Operating Temperature40 to +85°C
Storage Temperature
Junction Temperature
Soldering Temperature
ESD Protection (Input) 2000 V min (HBM)

Stresses greater than those listed under MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

### **Electrical Specifications**

#### **Recommended Operation Conditions**

Parameter	Min.	Тур.	Max.	Unit
Ambient Operating Temperature	-40		+85	°C
Power Supply Voltage (measured in respect to GND)	+3.0		+3.6	V

#### **DC Characteristics** ( $V_{DD} = 3.3V \pm 10\%$ , $T_A = -40^{\circ}C$ to $+85^{\circ}C$ )

Symbol	Parameter	Conditions		Min.	Тур.	Max.	Unit
V <sub>DD</sub>	Supply Voltage			3.0	3.3	3.6	V
V <sub>IH</sub>	Input High Voltage <sup>(1)</sup>	OE		2.0		V <sub>DD</sub> +0.3	V
V <sub>IL</sub>	Input Low Voltage <sup>(1)</sup>	OE		GND -0.3		0.8	V
I <sub>IL</sub> II	Input Leakage Current	$0 < Vin < V_{DD}$	With input pull-up and pull-downs	-20		20	
			Without input pull- up and pull-downs	-5		5	μΑ
I <sub>DD</sub>	On anotin a Summlar Cumunt	$R_{L} = 50\Omega, C_{L} = 2pF$ $OE = LOW$				95	mA
I <sub>DDOE</sub>	Operating Supply Current					50	mA
C <sub>IN</sub>	Input Capacitance	nput Capacitance @ 55MHz				7	pF
Cout	Output Capacitance	put Capacitance @ 55MHz				6	pF
L <sub>PIN</sub>	Pin Inductance					5	nH
R <sub>OUT</sub>	Output Resistance	CLK Outputs		3.0			kΩ

#### Notes:

1. Single edge is monotonic when transitioning through region.





#### Symbol Parameter Conditions Min. Unit Typ. Max. 25 MHz $F_{IN}$ Input Frequency 25 200 MHz Vout Output Frequency 100 MHz HCSL output @ V<sub>DD</sub> = Output High Voltage (1,2) 800 900 660 mV Voh 3.3V Output Low Voltage<sup>(1,2)</sup> 0 Vol -150 mV Crossing Point Voltage<sup>(1,2)</sup> Absolute 250 350 550 mV VCPA Crossing Point Voltage<sup>(1,2,4)</sup> Variation over all edges 140 mV VCN Jitter, Cycle-to-Cycle<sup>(1,3)</sup> 35 60 Jcc ps PCIe 2.0 Test Method @ 100MHz PCIe RMS Jitter 3.1 Jrms ps Output MF Modulation Frequency Spread Spectrum 30 31.5 33 kHz Rise Time(1,2) From 0.175V to 0.525V 175 500 tor ps Fall Time<sup>(1,2)</sup> From 0.525V to 0.175V 175 500 toF ps Skew between outputs At Crossing Point Voltage 50 TSKEW ps Duty Cycle<sup>(1,3)</sup> T<sub>DUTY-CYCLE</sub> 45 55 % TOE Output Enable Time<sup>(5)</sup> All outputs 10 μs Output Disable Time<sup>(5)</sup> All outputs 10 TOT μs From power-up to V<sub>DD</sub>=3.3V From Power-up V<sub>DD</sub>=3.3V 3.0 ms **t**STABLE Setting period after spread change Setting period after spread change 3.0 **t**SPREAD ms

#### HCSL Output AC Characteristics ( $V_{DD} = 3.3V \pm 10\%$ , $T_A = -40$ °C to +85°C)

Notes:

1.  $R_L = 50$ -Ohm with  $C_L = 2 pF$ 

2. Single-ended waveform

3. Differential waveform

4. Measured at the crossing point

5. CLK pins are tri-stated when OE is LOW

#### **Thermal Characteristics**

Symbol	Parameter	Conditions	Min.	Тур.	Max.	Unit
$\theta_{JA}$	Thermal Resistance Junction to Ambient	Still air			90	°C/W
$\theta_{JC}$	Thermal Resistance Junction to Case				24	°C/W

#### **Recomended Crystal Specification**

Pericom recommends:

a) GC2500003 XTAL 49S/SMD(4.0 mm), 25M, CL=18pF, +/-30ppm http://www.pericom.com/pdf/datasheets/se/GC\_GF.pdf

b) FY2500081, SMD 5x3.2(4P), 25M, CL=18pF, +/-30ppm

http://www.pericom.com/pdf/datasheets/se/FY\_F9.pdf

c) FL2500047, SMD 3.2x2.5(4P), 25M, CL=18pF, +/-20ppm

http://www.pericom.com/pdf/datasheets/se/FL.pdf





# Packaging Mechanical: 16-Pin TSSOP (L)



16-0061





### Packaging Mechanical: 16-Pin QSOP (Q)



16-0056

#### For latest package info.

please check: http://www.diodes.com/design/support/packaging/pericom-packaging/packaging-mechanicals-and-thermal-characteristics/

### **Ordering Information**

Ordering Code	Package Code	Package Type
PI6C557-03ALE	L	16-pin, 173mil Wide (TSSOP)
PI6C557-03ALEX	L	16-pin, 173mil Wide (TSSOP), Tape & Reel
PI6C557-03AQE	Q	16-pin, 150mil Wide (QSOP)
PI6C557-03AQEX	Q	16-pin, 150mil Wide (QSOP), Tape & Reel

Notes:

Thermal characteristics can be found on the company web site at www.diodes.com/design/support/packaging/

- E = Pb-free and Green ٠
- Adding an X suffix = Tape/Reel





#### IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.

Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

#### LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

A. Life support devices or systems are devices or systems which:

1. are intended to implant into the body, or

2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.

B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the

failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2016, Diodes Incorporated

www.diodes.com