Product Search Data Sheet




Note: This datasheet may be out of date. Please download the latest datasheet of MRMS611M from the official website of Murata Manufacturing Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=MRMS611M

## MRMS611M



## Appearance & Shape





(in mm)



## Packaging Information

Packaging	Specifications	Minimum Order Quantity
-	180mm Embossed Tape	5000

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date.

Please download the latest datashed of MRMS611M from the official website of Murata Manufacturing Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=MRMS611M

## MRMS611M



Operating Temperature Range	-40℃ to 85℃
Supply Voltage Range	1.6V to 3.5V
Low Level Output Voltage	0.2V
High Level Output Voltage	1.6V
Current Consumption(typ.)	3.0µA
Measure Condition of Current Consumption	Typ. Vcc1.8V
Operating Magnetic Field (Hon)	Max 1.8mT
Operating Magnetic Field (Hoff)	Min 1.2mT
Storage Temperature Range	-40.0°C to 125.0°C

This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



2 of 2