

#B953AS-5R6N=P3

Note: This datasheet may be out of date.

Please download the latest datasheet of #B953AS-5R6N=P3 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=%23B953AS-5R6N%3dP3
















Appearance & Shape







References

| Packaging | Specifications | Standard Packing Quantity |
|-----------|------------------|---------------------------------|
| =P3 | 330Embossed Tape | 500 |

| Mass (typ.) | | |
|-------------|--------|--|
| 1 piece | 3.688g | |



Notices

Rated current (Isat) is specified when the decrease of the initial inductance value at 10%. Rated current (Itemp) is specified when temperature of the inductor is raised 40°C by DC current.

1 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



#B953AS-5R6N=P3

Note: This datasheet may be out of date.

Please download the latest datasheet of #B953AS-5R6N=P3 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=%23B953AS-5R6N%3dP3



Specifications

| L size | 12.5±0.3mm |
|---|---------------|
| W size | 12.5±0.3mm |
| T size | 6.8mm |
| Size code inch (mm) | 4949 (125125) |
| Inductance | 5.6µH±30% |
| Inductance Test Frequency | 0.1MHz |
| Rated current (Isat) (Based on Inductance change) | 6800mA |
| Rated current (Itemp) (Based on Temperature rise) | 5600mA |
| Max. of DC resistance | 0.016Ω |
| Operating Temperature Range (Self-temperature rise is included) | -40°C to 85°C |
| Class of magnetic shield | Ferrite Core |
| Brand | Murata |
| Series | DS126C2 |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



FCTRONICS

Note: This datasheet may be out of date.


Please download the latest datasheet of #B953AS-5R6N=P3 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=%23B953AS-5R6N%3dP3

#B953AS-5R6N=P3



Characteristic Data





Impedance - Current Characteristics

Temperature Increase Characteristic

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

