

Note: This datasheet may be out of date. Please download the latest datasheet of LQW2BAS22NJ00# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=LQW2BAS22NJ00%23

"#" indicates a package specification code.

LQW2BAS22NJ00#


Size Code 2015 (0805) in mm (in inch), Horizontal Wound Type




< List of part numbers with package codes > LQW2BAS22NJ00B LQW2BAS22NJ00K LQW2BAS22NJ00L

Appearance & Shape







References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
К	330Embossed Tape	8000
L	180Embossed Tape	2000

Mass (typ.)		
1 piece	0.014g	

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





LQW2BAS22NJ00#

Note: This datasheet may be out of date. Please download the latest datasheet of LQW2BAS22NJ00# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=LQW2BAS22NJ00%23

"#" indicates a package specification code.



Specifications

L size	2.09±0.2mm
W size	1.53±0.2mm
T size	1.42±0.1mm
Size code inch (mm)	0805 (2015)
Inductance	22nH±5%
Inductance Test Frequency	250MHz
Rated current (Itemp) (Based on Temperature rise)	500mA
Max. of DC resistance	0.22Ω
Q(min.)	55
Q Test Frequency	500MHz
Self resonance frequency (min.)	2600MHz
Operating Temperature Range(Self-temperature rise is not included)	-55℃ to 125℃
Brand	Murata
Series	LQW2BAS_00

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.







Note: This datasheet may be out of date. Please download the latest datasheet of LQW2BAS22NJ00# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=LQW2BAS22NJ00%23

"#" indicates a package specification code.



LQW2BAS22NJ00#



Inductance - Frequency Characteristics

Q-Frequency Characteristics

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



3 of 3