

Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild_questions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or unavteries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is and its officers, employees, even if such claim any manner.

SEMICONDUCTOR

74AC151 • 74ACT151 8-Input Multiplexer

General Description

The AC/ACT151 is a high-speed 8-input digital multiplexer. It provides, in one package, the ability to select one line of data from up to eight sources. The AC/ACT151 can be used as a universal function generator to generate any logic function of four variables. Both true and complementary outputs are provided.

November 1988 Revised November 1999

Features


- I_{CC} reduced by 50%
- Outputs source/sink 24 mA
- ACT151 has TTL-compatible inputs

Ordering Code:


Order Number	Package Number	Package Description
74AC151SC	M16A	16-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150" Narrow Body
74AC151SJ	M16D	16-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
74AC151MTC	MTC16	16-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide
74AC151PC	N16E	16-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide
74ACT151SC	M16A	16-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150" Narrow Body
74ACT151SJ	M16D	16-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
74ACT151PC	N16E	16-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide

Device also available in Tape and Reel. Specify by appending suffix letter "X" to the ordering code.

Logic Symbols



Connection Diagram



Pin Descriptions

Pin Names	Description
I ₀ —I ₇	Data Inputs
S ₀ -S ₂	Select Inputs
E	Enable Input
Z	Data Output
Z	Inverted Data Output

FACT™ is a trademark of Fairchild Semiconductor Corporation.

© 1999 Fairchild Semiconductor Corporation DS009927

74AC151 • 74ACT151

Truth Table Inputs Outputs z Ε S₂ S_1 S₀ z н Х Х Х Н L L L ī₀ L L I_0 **T**₁ L L L Н I_1 L L н L \overline{I}_2 I_2 н н Ī₃ L L I_3 \overline{I}_4 н L L L I_4 н н 1₅ L L I_5 L ٦₆ L н н I_6 н 1₇ н н I_7 L


H = HIGH Voltage Level L = LOW Voltage Level X = Immaterial

Functional Description

The AC/ACT151 is a logic implementation of a single pole, 8-position switch with the switch position controlled by the state of three Select inputs, S_0 , S_1 , S_2 . Both true and complementary outputs are provided. The Enable input (\overline{E}) is active LOW. When it is not activated, the complementary output is HIGH and the true output is LOW regardless of all other inputs. The logic function provided at the output is:

 $\begin{aligned} Z &= \overline{E} \bullet (I_0 \bullet \overline{S}_0 \bullet \overline{S}_1 \bullet \overline{S}_2 + I_1 \bullet S_0 \bullet \overline{S}_1 \bullet \overline{S}_2 + \\ I_2 \bullet \overline{S}_0 \bullet S_1 \bullet \overline{S}_2 + I_3 \bullet S_0 \bullet S_1 \bullet \overline{S}_2 \overline{+} I_4 \bullet \overline{S}_0 \bullet \overline{S}_1 \bullet S_2 + I_5 \bullet \\ S_0 \bullet \overline{S}_1 \bullet \overline{S}_2 \overline{+} I_6 \bullet \overline{S}_0 \bullet S_1 \bullet S_2 + I_7 \bullet S_0 \bullet S_1 \bullet S_2) \end{aligned}$

The AC/ACT151 provides the ability, in one package, to select from eight sources of data or control information. By proper manipulation of the inputs, the AC/ACT151 can provide any logic function of four variables and its complement.



Absolute Maximum R	atings(Note 1)	Recommended Operating			
Supply Voltage (V _{CC})	-0.5V to +7.0V	Conditions			
DC Input Diode Current (I _{IK})		Supply Voltage (V _{CC})			
$V_{I} = -0.5V$	–20 mA	AC	2.0V to 6.0V		
$V_I = V_{CC} + 0.5V$	+20 mA	ACT	4.5V to 5.5V		
DC Input Voltage (V _I)	$-0.5 V$ to $V_{CC} + 0.5 V$	Input Voltage (V _I)	0V to V _{CC}		
DC Output Diode Current (I _{OK})		Output Voltage (V _O)	0V to V _{CC}		
$V_0 = -0.5V$	–20 mA	Operating Temperature (T _A)	-40°C to +85°C		
$V_O = V_{CC} + 0.5V$	+20 mA	Minimum Input Edge Rate (ΔV/Δt)			
DC Output Voltage (V _O)	–0.5V to V_{CC} + 0.5V	AC Devices			
DC Output Source		V_{IN} from 30% to 70% of V_{CC}			
or Sink Current (I _O)	±50 mA	V _{CC} @ 3.3V, 4.5V, 5.5V	125 mV/ns		
DC V _{CC} or Ground Current		Minimum Input Edge Rate ($\Delta V/\Delta t$)			
per Output Pin (I _{CC} or I _{GND})	±50 mA	ACT Devices			
Storage Temperature (T _{STG})	$-65^{\circ}C$ to $+150^{\circ}C$	V _{IN} from 0.8V to 2.0V			
Junction Temperature (T _J)		V _{CC} @ 4.5V, 5.5V	125 mV/ns		
PDIP	140°C	Note 1: Absolute maximum ratings are those va to the device may occur. The databook specific out exception, to ensure that the system desig supply, temperature, and output/input loading v recommend operation of FACT ^m circuits outside	ations should be met, with- n is reliable over its power ariables. Fairchild does not		

DC Electrical Characteristics for AC

Symbol	Parameter	V _{cc}	T _A = -	⊦25°C	$T_A = -40^{\circ}C$ to $+85^{\circ}C$	Units	Conditions	
Symbol	Parameter	(V)	Тур	Gu	aranteed Limits	Units	Conditions	
V _{IH}	Minimum HIGH Level	3.0	1.5	2.1	2.1		$V_{OUT} = 0.1V$	
	Input Voltage	4.5	2.25	3.15	3.15	V	or $V_{CC} - 0.1V$	
		5.5	2.75	3.85	3.85			
V _{IL}	Maximum LOW Level	3.0	1.5	0.9	0.9		$V_{OUT} = 0.1V$	
	Input Voltage	4.5	2.25	1.35	1.35	V	or $V_{CC} - 0.1V$	
		5.5	2.75	1.65	1.65			
√ _{ОН}	Minimum HIGH Level	3.0	2.99	2.9	2.9			
	Output Voltage	4.5	4.49	4.4	4.4	V	$I_{OUT} = -50 \ \mu A$	
		5.5	5.49	5.4	5.4			
							$V_{IN} = V_{IL} \text{ or } V_{IH}$	
		3.0		2.56	2.46		$I_{OH} = -12 \text{ mA}$	
		4.5		3.86	3.76	V	I _{OH} = -24 mA	
		5.5		4.86	4.76		I _{OH} = -24 mA(Note 2	
V _{OL}	Maximum LOW Level	3.0	0.002	0.1	0.1			
	Output Voltage	4.5	0.001	0.1	0.1	V	$I_{OUT} = 50 \ \mu A$	
		5.5	0.001	0.1	0.1			
							$V_{IN} = V_{IL} \text{ or } V_{IH}$	
		3.0		0.36	0.44		$I_{OL} = 12 \text{ mA}$	
		4.5		0.36	0.44	V	$I_{OL} = 24 \text{ mA}$	
		5.5		0.36	0.44		I _{OL} = 24 mA (Note 2)	
I _{IN} Note 4)	Maximum Input Leakage Current	5.5		±0.1	±1.0	μΑ	$V_I = V_{CC}, GND$	
OLD	Minimum Dynamic	5.5			75	mA	$V_{OLD} = 1.65V \text{ Max}$	
I _{ОНD}	Output Current (Note 3)	5.5			-75	mA	V _{OHD} = 3.85V Min	
I _{CC} Note 4)	Maximum Quiescent Supply Current	5.5		4.0	40.0	μA	$V_{IN} = V_{CC} \text{ or } GND$	

Note 3: Maximum test duration 2.0 ms, one output loaded at a time.

Note 4: $I_{\rm IN}$ and $I_{\rm CC}$ @ 3.0V are guaranteed to be less than or equal to the respective limit @ 5.5V $V_{\rm CC}.$

Symbol	Parameter	V _{CC}	$T_A = +25^{\circ}C$		$T_A = -40^{\circ}C \text{ to } +85^{\circ}C$	Units	Conditions	
Symbol	rarameter	(V)	Тур	Gu	aranteed Limits	onita	Conditions	
V _{IH}	Minimum HIGH Level	4.5	1.5	2.0	2.0	V	$V_{OUT} = 0.1V$	
	Input Voltage	5.5	1.5	2.0	2.0		or $V_{CC} - 0.1V$	
VIL	Maximum LOW Level	4.5	1.5	0.8	0.8	V	V _{OUT} = 0.1V	
	Input Voltage	5.5	1.5	0.8	0.8		or $V_{CC} - 0.1V$	
V _{OH}	Minimum HIGH Level	4.5	4.49	4.4	4.4	V	L 50A	
	Output Voltage	5.5	5.49	5.4	5.4	v	$I_{OUT} = -50 \ \mu A$	
							$V_{IN} = V_{IL} \text{ or } V_{IH}$	
		4.5		3.86	3.76	V	$I_{OH} = -24 \text{ mA}$	
		5.5		4.86	4.76		I _{OH} = -24 mA (Note 5	
V _{OL}	Maximum LOW Level	4.5	0.001	0.1	0.1	V	50.4	
	Output Voltage	5.5	0.001	0.1	0.1	v	I _{OUT} = 50 μA	
							$V_{IN} = V_{IL} \text{ or } V_{IH}$	
		4.5		0.36	0.44	V	$I_{OL} = 24 \text{ mA}$	
		5.5		0.36	0.44		I _{OL} = 24 mA (Note 5)	
I _{IN}	Maximum Input	5.5		±0.1	±1.0	μA	$V_I = V_{CC}, GND$	
	Leakage Current	5.5		±0.1	±1.0	μΑ	vi – v _{CC} , Gind	
I _{CCT}	Maximum	5.5	0.6		1.5	mA	$V_{I} = V_{CC} - 2.1V$	
	I _{CC} /Input	5.5	0.0		1.5		v1 = vCC = 2.1V	
I _{OLD}	Minimum Dynamic	5.5			75	mA	V _{OLD} = 1.65V Max	
I _{OHD}	Output Current (Note 6)	5.5			-75	mA	V _{OHD} = 3.85V Min	
I _{CC}	Maximum Quiescent	5.5		4.0	40.0		$V_{IN} = V_{CC}$	
	Supply Current	5.5	4.	4.0	40.0	μA	or GND	

Note 5: All outputs loaded; thresholds on input associated with output under test.

Note 6: Maximum test duration 2.0 ms, one output loaded at a time.

AC Electrical Characteristics for AC

Symbol		V _{cc}	T _A = +25°C C _L = 50 pF			$T_A = -40^{\circ}C \text{ to } +85^{\circ}C$ $C_L = 50 \text{ pF}$		Units
	Parameter	(V)						
		(Note 7)	Min	Тур	Max	Min	Max	I
t _{PLH}	Propagation Delay	3.3	3.0	11.5	18.0	3.0	20.0	ns
	S_n to Z or Z	5.0	2.5	8.5	13.0	2.0	15.0	115
t _{PHL}	Propagation Delay	3.3	2.5	12.0	18.0	2.5	20.0	ns
	S_n to Z or \overline{Z}	5.0	2.0	8.5	13.0	1.5	15.0	
t _{PLH}	Propagation Delay	3.3	2.5	8.0	13.0	2.0	14.0	ns
	E to Z or Z	5.0	2.0	6.0	10.0	1.5	11.0	115
t _{PHL}	Propagation Delay	3.3	1.5	8.5	13.0	1.5	14.0	ns
	E to Z or Z	5.0	1.5	6.5	10.0	1.5	11.0	ns
t _{PLH}	Propagation Delay	3.3	2.5	9.5	14.0	2.0	15.5	
	I_n to Z or \overline{Z}	5.0	1.5	7.0	10.5	1.5	11.0	ns
t _{PHL}	Propagation Delay	3.3	2.5	9.5	15.0	2.0	16.0	ns
	I _n to Z or Z	5.0	1.5	7.0	11.0	1.5	12.0	ns

Note 7: Voltage Range 3.3 is $3.3V \pm 0.3V$

Voltage Range 5.0 is 5.0V $\pm\,0.5V$


		V _{cc}		$T_A = +25^{\circ}C$		$T_A = -40^{\circ}C \text{ to } +85^{\circ}C$		
Symbol	Parameter	(V)	$C_L = 50 \text{ pF}$			$C_L = 50 \text{ pF}$		Units
		(Note 8)	Min	Тур	Max	Min	Max	
t _{PLH}	Propagation Delay S _n to Z	5.0	3.5	12.5	15.5	3.0	17.0	ns
t _{PHL}	Propagation Delay S _n to Z	5.0	3.5	12.5	15.5	3.0	16.5	ns
t _{PLH}	Propagation Delay S_n to \overline{Z}	5.0	3.5	12.5	15.0	3.0	16.5	ns
t _{PHL}	Propagation Delay S_n to \overline{Z}	5.0	4.0	12.5	16.5	3.5	18.5	ns
t _{PLH}	Propagation Delay E to Z	5.0	2.5	6.0	9.5	2.5	10.0	ns
t _{PHL}	Propagation Delay E to Z	5.0	2.5	6.0	9.0	2.5	10.0	ns
t _{PLH}	Propagation Delay E to Z	5.0	2.5	6.0	8.5	2.5	9.5	ns
t _{PHL}	Propagation Delay E to Z	5.0	3.0	6.5	10.0	2.5	10.5	ns
t _{PLH}	Propagation Delay I _n to Z	5.0	3.5	7.5	11.5	3.0	12.5	ns
t _{PHL}	Propagation Delay I _n to Z	5.0	3.5	8.0	12.0	3.0	13.5	ns
t _{PLH}	Propagation Delay I_n to \overline{Z}	5.0	3.5	8.0	12.0	3.0	13.0	ns
t _{PHL}	Propagation Delay I_n to \overline{Z}	5.0	4.0	8.0	12.5	3.0	14.0	ns


Note 8: Voltage Range 5.0 is $5.0V \pm 0.5V$


Capacitance


Symbol	Parameter	Тур	Units	Conditions
C _{IN}	Input Capacitance	4.5	pF	V _{CC} = OPEN
C _{PD}	Power Dissipation Capacitance	70.0	pF	$V_{CC} = 5.0V$

74AC151 • 74ACT151









ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor haves against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death a

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

Downloaded from Arrow.com.